

Supplementary test data to the 3200-44 chart dated 9-1-55 for the Model 532-533-533DM-534-534A-534B-600 Tube Testers is as follows:

TUBE	FIL	SELECTORS	BIAS	ENG	PRESS	AVER. MUT. COND.	NOTATIONS
4BS8	4.3	EV-7608-9	20	86	P4	4000	Triode No. 1
4BS8	4.3	EV-2103-9	20	86	P4	4000	Triode No. 2
5AV8	5.0	EV-6987-0	9	86	P4	4000	Pent. Sect.
5AV8	5.0	EV-2301-0	21	83	P4	3300	Triode Sect.
6BE8	6.3	EV-9678-3	15	76	P4	2250	Pent. Sect. Shcrt on 2-3
6BE8	6.3	EV-1203-0	16	87	P4	4500	Triode Sect.
6BH8	6.3	EV-7986-0	11	87	P4	4500	Pent. Sect.
6BH8	6.3	EV-2301-0	27	83	P4	3300	Triode Sect.
6BJ8	6.3	EV-8709-0	24	80	P4	2800	Triode Sect.
6BJ8	6.3	EV-0603-0	0	61	P1☆	---	Diode No. 1
6BJ8	6.3	EV-0102-0	0	61	P1☆	---	Diode No. 2
6BS8	6.3	EV-7608-9	20	86	P4	4000	Triode No. 1
6BS8	6.3	EV-2103-9	20	86	P4	4000	Triode No. 2
6BW4	6.3	EV-0709-1	0	20	P3	---	Plate No. 1
6BW4	6.3	EV-0109-7	0	20	P3	---	Plate No. 2
6CH7	6.3	EV-7608-0	18	88	P4	5000	Triode No. 1
6CH7	6.3	EV-2103-0	18	88	P4	5000	Triode No. 2
6CM7	6.3	EV-7603-0	24	73	P4	2000	Triode No. 1
6CM7	6.3	EV-8109-0	20	87	P4	4400	Triode No. 2
6CS7	6.3	EV-7608-0	17	75	P4	2200	Triode No. 1
6CS7	6.3	EV-3109-0	24	87	P4	4500	Triode No. 2
6DN6	6.3	JR-5073-0	43	90	P4	6000	CAP=P
6DQ6	6.3	JR-5047-0	32	90	P4	6000	CAP=P
12AB5	12.6	EV-3917-0	21	85	P4	3700	
12DQ6	12.6	JR-5047-0	32	90	P4	6000	CAP=P
25DN6	25.0	JR-5073-0	43	90	P4	6000	CAP=P
25DQ6	25.0	JR-5047-0	32	90	P4	6000	CAP=P
X-155	6.3	EV-7608-9	20	86	P4	4000	Triode No. 1
X-155	6.3	EV-2103-9	20	86	P4	4000	Triode No. 2
5851	2.5	HR-8360-0	30	67	P4	1600	
6397	2.5	HR-8360-0	30	72	P4	1950	

Supplementary test data to the 3200-47 chart dated 9-1-55 for the Model 533A-533DM (Series 600) 535-600A-605-605A Tube Testers is as follows:

TUBE	FIL	SELECTORS	BIAS	ENG	PRESS	AVER. MUT. COND.	NOTATIONS
4BS8	4.3	EV-7608-9	19	87	P4	4500	Triode No. 1
4BS8	4.3	EV-2103-9	19	87	P4	4500	Triode No. 2
5AV8	5.0	EV-6987-0	7	86	P4	4000	Pent. Sect.
5AV8	5.0	EV-2301-0	24	83	P4	3300	Triode Sect.
6BE8	6.3	EV-9678-3	7	80	P4	2800	Pent. Sect. Shorts on 23
No Shorts for Testers having Serial Numbers above 135-, 136-, or 138-10000							
6BE8	6.3	EV-1203-0	12	90	P4	6200	Triode Sect.
6BH8	6.3	EV-7986-0	7	88	P4	5000	Pent. Sect.
6BH8	6.3	EV-2301-0	27	83	P4	3300	Triode Sect.

TUBE	FIL	SELECTORS	BIAS	ENG	PRESS	AVER. MUT. COND.	NOTATIONS
6BJ8	6.3	EV-8709-0	27	80	P4	2800	Triode Sect.
6BJ8	6.3	EV-0603-0	0	78	P1☆	---	Diode No. 1
6BJ8	6.3	EV-0102-0	0	78	P1☆	---	Diode No. 2
6BS8	6.3	EV-7608-9	19	87	P4	4500	Triode No. 1
6BS8	6.3	EV-2103-9	19	87	P4	4500	Triode No. 2
6BW4	6.3	EV-0709-1	0	20	P3		Plate No. 1
6BW4	6.3	EV-0109-7	0	20	P3		Plate No. 2
6CH7	6.3	EV-7608-0	15	91	P4	6800	Triode No. 1
6CH7	6.3	EV-2103-0	15	91	P4	6800	Triode No. 2
6CM7	6.3	EV-7603-0	27	73	P4	2000	Triode No. 1
6CM7	6.3	EV-8109-0	24	87	P4	4400	Triode No. 2
6CS7	6.3	EV-7608-0	22	75	P4	2200	Triode No. 1
6CS7	6.3	EV-3109-0	27	87	P4	4500	Triode No. 2
6DN6	6.3	JR-5073-0	28	93	—	2000	CAP=P Hold down P1 and Press P4
6DQ6	6.3	JR-5047-0	25	90	—	6000	CAP=P. Hold down P1 and Press P4.
12AB5	12.6	EV-3917-0	13	86	P4	4100	
12DQ6	12.6	JR-5047-0	25	90	—	6000	CAP=P. Hold down P1 and Press P4.
25DN6	25.0	JR-5073-0	28	93	—	9000	CAP=P. Hold down P1 and Press P4.
25DQ6	25.0	JR-5047-0	25	90	—	6000	CAP=P. Hold down P1 and Press P4.
X-155	6.3	EV-7608-9	20	88	P4	5000	Triode No. 1
X-155	6.3	EV-2103-9	20	88	P4	5000	Triode No. 2
5851	2.5	HR-8360-0	33	67	P4	1600	
6397	2.5	HR-8360-0	33	72	P4	1950	

Supplementary test data to the 3200-43 chart dated 9-1-55 for the Model 536
538-538A Tube Testers is as follows:

TUBE	FIL	SELECTORS	BIAS	ENG	PRESS	MIN MUT. COND.	NOTATIONS
4BS8	4.3	EV-7608-9	15	Low Sig.	P4	3800	Triode No. 1
4BS8	4.3	EV-2103-9	15	Low Sig.	P4	3800	Triode No. 2
5AV8	5.0	EV-6987-0	7	Low Sig.	P4	3900	Pent. Sect.
5AV8	5.0	EV-2301-0	22	Low Sig.	P4	2100	Triode Sect.
6BE8	6.3	EV-9678-3	9	Low Sig.	P4	2400	Pent. Sect. Short on 2-3
6BE8	6.3	EV-1203-0	8	Low Sig.	P4	5000	Triode Sect.
6BH8	6.3	EV-7986-0	10	Low Sig.	P4	3800	Pent Sect.
6BH8	6.3	EV-2301-0	25	Low Sig.	P4	2100	Triode Sect.
6BJ8	6.3	EV-8709-0	25	Low Sig.	P4	1750	Triode Sect.
6BJ8	6.3	EV-0603-0	0	61	P1	---	Diode No. 1
6BJ8	6.3	EV-0102-0	0	61	P1	---	Diode No. 2
6BS8	6.3	EV-7608-9	15	Low Sig.	P4	3800	Triode No. 1
6BS8	6.3	EV-2103-9	15	Low Sig.	P4	3800	Triode No. 2
6BW4	6.3	EV-0709-1	0	20	P3	---	Plate No. 1
6BW4	6.3	EV-0109-7	0	20	P3	---	Plate No. 2
6CH7	6.3	EV-7608-0	17	Low Sig.	P4	4300	Triode No. 1
6CH7	6.3	EV-2103-0	17	Low Sig.	P4	4300	Triode No. 2
6CM7	6.3	EV-7603-0	24	—	P4	1260	Triode No. 1
6CM7	6.3	EV-8109-0	20	—	P4	2800	Triode No. 2

TUBE	FIL	SELECTORS	BIAS	ENG	PRESS	MIN MUT. COND.	NOTATIONS
6CS7	6.3	EV-7608-0	17	—	P4	1400	Triode No. 1
6CS7	6.3	EV-3109-0	24	—	P4	2840	Triode No. 2
6DN6	6.3	JR-5073-0	43	—	P4	3800	CAP=P
6DQ6	6.3	JR-5047-0	40	—	P4	3800	CAP=P
12AB5	12.6	EV-3917-0	21	—	P4	2300	
12DQ6	12.6	JR-5047-0	40	—	P4	3800	CAP=P
25DN6	25.0	JR-5073-0	43	—	P4	3800	CAP=P
25DQ6	25.0	JR-5074-0	40	—	P4	3800	CAP=P
X-155	6.3	EV-7608-9	14	Low Sig.	P4	3800	Triode No. 1
X-155	6.3	EV-2103-9	14	Low Sig.	P4	3800	Triode No. 2
5851	2.5	HR-8360-0	33	Low Sig.	P4	1000	
6397	2.5	HR-8360-0	33	Low Sig.	P4	1200	

- - - - -

Supplementary test data to the 3200-42 chart dated 2-1-55 for the Model 539A Tube Tester is as follows:

TUBE	FIL	SELECTORS	BIAS VOLTS	SHUNT	PRESS	RANGE	MIN. MUT. COND.	NOTATIONS
4BS8	4.3	EV-7608-9	2.5	—	P4	B	4500	Triode No. 1
4BS8	4.3	EV-2103-9	2.5	—	P4	B	4500	Triode No. 2
5AV8	5.0	EV-6987-0	0.8	—	P4	B	3900	Pent. Sect.
5AV8	5.0	EV-2301-0	4.6	—	P4	C	2100	Triode Sect.
6BE8	6.3	EV-9678-3	0.8	—	P4	C	2400	Pent. Sect.
Short on 2-3 for testers having serial numbers below 130-10000								
6BE8	6.3	EV-1203-0	1.2	—	P4	B-	5350	Triode Sect.
6BH8	6.3	EV-7986-0	0.8	—	P4	B	4400	Pent Sect.
6BH8	6.3	EV-2301-0	5.7	—	P4	C	2100	Triode Sect.
6BJ8	6.3	EV-8709-0	5.7	—	P4	C	1750	Triode Sect.
6BJ8	6.3	EV-0603-0	0.0	0	P1	F	☆	Diode No. 1
6BJ8	6.3	EV-0102-0	0.0	0	P1	F	☆	Diode No. 2
6BS8	6.3	EV-7608-9	2.5	—	P4	B	4500	Triode No. 1
6BS8	6.3	EV-2103-9	2.5	—	P4	B	4500	Triode No. 2
6BW4	6.3	EV-0709-1	0.0	50	P3	F	☆	Plate No. 1
6BW4	6.3	EV-0109-7	0.0	50	P3	F	☆	Plate No. 2
6CH7	6.3	EV-7608-0	2.8	—	P4	B	4300	Triode No. 1
6CH7	6.3	EV-2103-0	2.8	—	P4	B	4300	Triode No. 2
6CM7	6.3	EV-7603-0	5.6	—	P4	C	1260	Triode No. 1
6CM7	6.3	EV-8109-0	4.5	—	P4	B	2800	Triode No. 2
6CS7	6.3	EV-7608-0	4.5	—	P4	C	1400	Triode No. 1
6CS7	6.3	EV-3109-0	6.0	—	P4	B	2840	Triode No. 2
6DN6	6.3	JR-5073-0	7.5	—	—	B	5650	CAP=P. Hold down Pl and Press P4.
6DQ6	6.3	JR-5047-0	12.0	—	P4	B	3800	CAP=P
12AB5	12.6	EV-3917-0	2.2	—	P4	D	2600	
12DQ6	12.6	JR-5047-0	12.0	—	P4	B	3800	CAP=P
25DN6	25.0	JR-5073-0	7.5	—	—	B	5650	CAP=P Hold down Pl and Press P4
25DQ6	25.0	JR-5047-0	12.0	—	P4	B	3800	CAP=P
X-155	6.3	EV-7608-9	1.7	—	P4	B	5000	Triode No. 1
X155	6.3	EV-2103-9	1.7	—	P4	B	5000	Triode No. 2
5851	2.5	HR-8360-0	9.0	—	P4	E	1000	
6397	2.5	HR-8360-0	8.5	—	P4	E	1200	

We trust this information will be of value to you.

THE HICKOK ELECTRICAL INST. CO.
10514 Dupont Ave.
Cleveland, 8, Ohio