

Master Dial Belt Index

First Edition - April 14, 1999

Second Edition - April 13, 2003

Copyright © 1999, 2003, 2004, 2005, 2006, 2012 by Dale H. Cook

Star City Antique Radios and Test Equipment

<http://plymouthcolony.net/starcity/radios/radtop.html>

starcity@plymouthcolony.net

This index is compiled from *G-C No. 345 Radio Dial Belt, Drive Cable and Cabinet Repair Guide* (1945) and *JFD Dial Belt Manual* (1946). Some models are found in only one guide. Note that Walsco belt numbers are the same as G-C numbers with an extra "1" in front (i.e. a Walsco 1131 is the same as a G-C 131).

When a set uses more than one belt there are multiple entries for that set followed by one of these indicators: *C - Condenser *D - Dial *M - Motor.

Following the index are listings of the belts in the G-C and JFD lines with inside and cut dimensions. There are also competitive interchange charts.

Please email any comments or corrections to starcity@plymouthcolony.net.

Dial Belt Index

Model	G-C Belt	Circumference Around Pulleys	JFD Belt	Circumference Around Pulleys
ACRATEST				
AM29C	109	8-1/2"	9	8-17/32"
AM79H	109	8-1/2"	9	8-17/32"
AM111G	109	8-1/2"	9	8-17/32"
24BH	108	8-21/32"	8	8-9/16"
24BW	108	8-21/32"	8	8-9/16"
30C	109	8-1/2"	9	8-17/32"
31C	109	8-1/2"	9	8-17/32"

ADMIRAL - Straight Face Chassis

AM3	139	12-9/32"	67	12-1/4"
AM3-86-57	139	12-9/32"	67	12-1/4"
AM4	139	12-9/32"	67	12-1/4"
AM4-58	139	12-9/32"	67	12-1/4"
AM5	139	12-9/32"	67	12-1/4"
AM6	139	12-9/32"	67	12-1/4"
AM6-86-57	139	12-9/32"	67	12-1/4"
AM7	139	12-9/32"	67	12-1/4"
AM7-86	139	12-9/32"	67	12-1/4"
AM8	139	12-9/32"	67	12-1/4"
AM8-59	139	12-9/32"	67	12-1/4"

Model	G-C Belt	Circumference Around Pulleys	JFD Belt	Circumference Around Pulleys
-------	----------	------------------------------	----------	------------------------------

ADMIRAL - Straight Face Chassis Continued

AM3	138	11-57/64"	69	11-29/32"
AM3-87-88	138	11-57/64"	69	11-29/32"

ADMIRAL - Tilt Face Chassis

AM4	138	11-57/64"	69	11-29/32"
AM4-88	138	11-57/64"	69	11-29/32"
AM5	138	11-57/64"	69	11-29/32"
AM6	138	11-57/64"	69	11-29/32"
AM6-87-88	138	11-57/64"	69	11-29/32"
AM7	138	11-57/64"	69	11-29/32"
AM7-87	138	11-57/64"	69	11-29/32"
AM8	138	11-57/64"	69	11-29/32"
AM8-89	138	11-57/64"	69	11-29/32"
F3	139	12-9/32"	39	12-7/16"
8K	170	16-19/64"	87	16-3/16"
8KU	170	16-19/64"	87	16-3/16"
8T	170	16-19/64"	87	16-3/16"
8TU	170	16-19/64"	87	16-3/16"
9G	169	17-13/32"	68	17-7/16"
11-A	169	17-13/32"	68	17-7/16"
11-S	169	17-13/32"	68	17-7/16"
14-S	169	17-13/32"	68	17-7/16"
16R	169	17-13/32"	68	17-7/16"
16S	169	17-13/32"	68	17-7/16"
16V	169	17-13/32"	68	17-7/16"
86	139	12-9/32"	67	12-1/4"
139-11A	169	17-13/32"	68	17-7/16"
140-16S	169	17-13/32"	68	17-7/16"
144-11A	169	17-13/32"	68	17-7/16"
144-16S	169	17-13/32"	68	17-7/16"

AIRLINE (Montgomery Ward)

62-179	163	9-19/64"	16	9-7/16"
62-180	163	9-19/64"	63	9-3/8"
62-182	163	9-19/64"	63	9-3/8"
62-185	163	9-19/64"	63	9-3/8"
62-187	163	9-19/64"	63	9-3/8"
62-190	163	9-19/64"	16	9-7/16"
62-192	164	10-1/4"	63	9-3/8"
62-194	163	9-19/64"	16	9-7/16"
62-195	164	10-1/4"	64	10-3/16"
62-196	163	9-19/64"	16	9-7/16"
62-197	164	10-1/4"	64	10-3/16"
62-206	163	9-19/64"	16	9-7/16"
62-207	163	9-19/64"	63	9-3/8"
62-209	163	9-19/64"	63	9-3/8"
62-215	163	9-19/64"	16	9-7/16"

Model	G-C Belt	Circumference Around Pulleys	JFD Belt	Circumference Around Pulleys
AIRLINE (Montgomery Ward) Continued				
62-216	163	9-19/64"	16	9-7/16"
62-218	163	9-19/64"	63	9-3/8"
62-220	163	9-19/64"	63	9-3/8"
62-221	163	9-19/64"	63	9-3/8"
62-223	163	9-19/64"	63	9-3/8"
62-226	192	Straight belt	51	16-1/2"
62-228	192	Straight belt	51	16-1/2"
62-249	163	9-19/64"	23	10-1/3"
62-250	192	Straight belt	51	16-1/2"
62-251	123	9-7/8"	27	9-15/16"
62-253	123	9-7/8"	66	9-7/8"
62-255	123	9-7/8"	23	10-1/3"
62-257	123	9-7/8"	23	10-1/3"
62-259	192	Straight belt	51	16-1/2"
62-301	159	8-1/32"	4	8-3/32"
62-301X	159	8-1/32"	4	8-3/32"
62-303	131W	11-9/32"	65	11-3/16"
62-307	123	9-7/8"	23	10-1/3"
62-308	192	Straight belt	92	15-13/16"
62-309	131W	11-9/32"	65	11-3/16"
62-316	123	9-7/8"	23	10-1/3"
62-317	123	9-7/8"	23	10-1/3"
62-318	192	Straight belt	51	16-1/2"
62-328	123	9-7/8"	23	10-1/3"
62-338	123	9-7/8"	23	10-1/3"
62-358	184	16-27/64"	51	16-1/2"
62-368	184	16-27/64"	51	16-1/2"
62-407	123	9-7/8"	23	10-1/3"
62-408	192	Straight belt	92	15-13/16"
62-409	192	Straight belt	51	16-1/2"
62-416	123	9-7/8"	23	10-1/3"
62-418	192	Straight belt	51	16-1/2"
62-428	123	9-7/8"	23	10-1/3"
62-430	123	9-7/8"	23	10-1/3"
62-448	184	16-27/64"	51	16-1/2"
62-458	184	16-27/64"	51	16-1/2"

AIRMASTER

All Models	114	8-15/64"	62	8-1/4"
------------	-----	----------	----	--------

ARVIN

617	185	16-15/16"	89	16-13/16"
617B	185	16-15/16"	89	16-13/16"
618B	147	14-27/64"	47	14-1/2"
627	185	16-15/16"	89	16-13/16"
627B	185	16-15/16"	89	16-13/16"
628B	147	14-27/64"	47	14-1/2"

Model	G-C Belt	Circumference Around Pulleys	JFD Belt	Circumference Around Pulleys
ARVIN Continued				
927	165	17-1/16"	89	16-13/16"
1127	165	17-1/16"	89	16-13/16"
1237	166	19-7/16"	90	19-9/16"
1237D	166	19-7/16"	90	19-9/16"
1247	166	19-7/16"	90	19-9/16"
1247A	166	19-7/16"	90	19-9/16"
1247D	166	19-7/16"	90	19-9/16"
1427	166	19-7/16"	90	19-9/16"
1427D	166	19-7/16"	90	19-9/16"
Part # 28-13838147		14-27/64"	94	14-27/64"
Part # 28-15647185		16-15/16"	93	16-15/16"

BELMONT

556	126	9-61/64"	19	9-13/16"
685	126	9-61/64"	19	9-13/16"
686	126	9-61/64"	26	10-1/16"
746A	126	9-61/64"	19	9-13/16"
770	126	9-61/64"	26	10-1/16"
778	126	9-61/64"	19	9-13/16"
786	126	9-61/64"	26	10-1/16"
787	126	9-61/64"	26	10-1/16"
822	126	9-61/64"	19	9-13/16"
845A	126	9-61/64"	19	9-13/16"
878	107	7-11/16"	4	8-3/32"
878A	107	7-11/16"	7	7-23/32"
878B	107	7-11/16"	7	7-23/32"
879	153	8-39/64"	53	8-11/16"
947	136	11-25/64"	95	11-25/64"
1070	126	9-61/64"	26	10-1/16"
1070B	126	9-61/64"	19	9-13/16"
1170	107	7-11/16"	4	8-3/32"
1170A	107	7-11/16"	7	7-23/32"
1170B	107	7-11/16"	3	7-17/32"
1170C	107	7-11/16"	7	7-23/32"
1171	153	8-39/64"	53	8-11/16"
1172	107	7-11/16"	4	8-3/32"
1172A	107	7-11/16"	7	7-23/32"
1174	107	7-11/16"	4	8-3/32"
112-125	126	9-61/64"	26	10-1/16"
112-176	107	7-11/16"	55	7-11/16"
112-194	153	8-39/64"	12	8-19/32"

BOSCH

660	129	10-41/64"	29	10-13/16"
670	115	9-13/64"	15	9-5/16"
670C	115	9-13/64"	15	9-5/16"
670S	115	9-13/64"	15	9-5/16"

Model	G-C Belt	Circumference Around Pulleys	JFD Belt	Circumference Around Pulleys
--------------	-----------------	-------------------------------------	-----------------	-------------------------------------

BOSCH Continued

678	115	9-13/64"	15	9-5/16"
680	115	9-13/64"	15	9-5/16"

CAPEHART

3650	157	7-1/64"	57	7-3/32"
------	-----	---------	----	---------

CASE

16SME	178	12-1/2"	40	12-5/16"
19A	178	12-1/2"	40	12-5/16"
19RSME	178	12-1/2"	40	12-5/16"
27SME	178	12-1/2"	40	12-5/16"
110RSME	178	12-1/2"	40	12-5/16"
701	178	12-1/2"	40	12-5/16"
801	178	12-1/2"	40	12-5/16"
802	178	12-1/2"	40	12-5/16"
1001	178	12-1/2"	40	12-5/16"
1101	178	12-1/2"	40	12-5/16"
1102	178	12-1/2"	40	12-5/16"

CORONADO (Gamble Skogmo, Inc.)

ODM	123	9-7/8"	66	9-7/8"
ODM-578	163	9-19/64"	66	9-7/8"
WG	123	9-7/8"	66	9-7/8"
8X35	163	9-19/64"	63	9-3/8"
8X36	164	10-1/4"	24	10-5/16"
11B	132	10-31/32"	21	10-3/4"
22CM576	164	10-1/4"	26	10-1/16"
26FM552	164	10-1/4"	26	10-1/16"
457	163	9-19/64"	16	9-7/16"
516	163	9-19/64"	16	9-7/16"
552	186	14-7/32"	47	14-1/2"
650A	186	14-7/32"	47	14-1/2"
686	126	9-61/64"	19	9-13/16"
740	126	9-61/64"	19	9-13/16"
770	126	9-61/64"	19	9-13/16"
778	126	9-61/64"	19	9-13/16"
787	126	9-61/64"	19	9-13/16"
810	126	9-61/64"	19	9-13/16"
822	126	9-61/64"	19	9-13/16"
850B	159	8-1/32"	11	7-29/32"
1170	107	7-11/16"	5	7-9/16"
17447	186	14-7/32"	47	14-1/2"
17514	159	8-1/32"	4	8-3/32"
17628	126	9-61/64"	26	10-1/16"

Model	G-C Belt	Circumference Around Pulleys	JFD Belt	Circumference Around Pulleys
-------	----------	------------------------------	----------	------------------------------

CORONADO (Gamble Skogmo, Inc.) Continued

17676	132	10-31/32"	32	11-1/16"
112-125	126	9-61/64"	26	10-1/16"
112-176	107	7-11/16"	55	7-11/16"
112-194	153	8-39/64"	12	8-19/32"

CROSLEY

636	141	11-3/4"	36	11-9/16"
726	194	11-21/32"	----	
816	141	11-3/4"	36	11-9/16"
916	141	11-3/4"	36	11-9/16"
1016	141	11-3/4"	78	12-1/32"
1117	158	6-15/16"	2	6-13/16"
1126	141	11-3/4"	36	11-9/16"
1127	158	6-15/16"	2	6-13/16"
1128	194	11-21/32"	36	11-9/16"
1137	158	6-15/16"	2	6-13/16"
1155	132	10-31/32"	52	10-9/16"
1216	141	11-3/4"	36	11-9/16"
1217	158	6-15/16"	2	6-13/16"
1227	158	6-15/16"	2	6-13/16"
1316	141	11-3/4"	36	11-9/16"
1336	141	11-3/4"	36	11-9/16"
1516	141	11-3/4"	36	11-9/16"
Manual Tuning				
All Models	141	11-3/4"	36	11-9/16"
Electric Tuning				
All Models	158	6-15/16"	58	6-3/4"

CROWE MFG. CO.

3187	167	8-13/16"	84	8-13/16"
3489	129	10-41/64"	20	10-11/16"
3594	187	15-17/64"	49	15-5/32"
3631	101	6-23/32"	1	6-5/8"
7457	117	9-1/16"	17	9-5/32"
7878	110	8-25/64"	13	8-5/8"
7879	102	6-57/64"	2	6-13/16"
9824	107	7-11/16"	55	7-11/16"
9905	114	8-15/64"	59	8-3/16"
10305	154	12-1/32"	78	12-1/32"
10565	105	7-1/2"	5	7-9/16"
11117	144	12-15/32"	39	12-7/16"
11165	116	9-5/16"	16	9-7/16"
11175	107	7-11/16"	7	7-23/32"
12704	188	19-47/64"	90	19-9/16"
13628	119	9-17/32"	16	9-7/16"
13636	123	9-7/8"	19	9-13/16"

Model	G-C Belt	Circumference Around Pulleys	JFD Belt	Circumference Around Pulleys
-------	----------	------------------------------	----------	------------------------------

CROWE MFG. CO. Continued

13755	190	17-5/8"	81	17-9/16"
13762	191	22-49/64"	74	22-9/16"
13841	189	18-1/2"	82	18-9/16"
14039	152	10-1/2"	22	10-1/2"

DE JUR AMSCO

10-608	101	6-23/32"	1	6-5/8"
10-609	136	11-25/64"	95	11-25/64"

DETROLA

155	136	11-25/64"	95	11-25/64"
163	135	11"	35	11-3/32"
164	135	11"	35	11-3/32"
165	135	11"	35	11-3/32"

DEWALD

901	141	11-3/4"	41	11-15/16"
1102	141	11-3/4"	41	11-15/16"

EMERSON

A	104	8-1/64"	59	8-3/16"
AA	103	7-15/32"	3	7-17/32"
AB	118	10-23/64"	18	10-15/32"
AC	104	8-1/64"	59	8-3/16"
AE	114	8-15/64"	14	8-7/16"
AF	106	7-1/4"	56	7-9/32"
AG	118	10-23/64"	18	10-15/32"
AH	106	7-1/4"	56	7-9/32"
AJ	104	8-1/64"	59	8-3/16"
AL	104	8-1/64"	59	8-3/16"
ALLW	156	7-9/32"	56	7-9/32"
AM	103	7-15/32"	3	7-17/32"
AP	156	7-9/32"	56	7-9/32"
AR	106	7-1/4"	56	7-9/32"
AS	106	7-1/4"	56	7-9/32"
AV	155	7-35/64"	3	7-17/32"
AW	156	7-9/32"	56	7-9/32"
B	103	7-15/32"	3	7-17/32"
BF	103	7-15/32"	3	7-17/32"
C	118	10-23/64"	18	10-15/32"
D	118	10-23/64"	18	10-15/32"
F	103	7-15/32"	3	7-17/32"

Model	G-C Belt	Circumference Around Pulleys	JFD Belt	Circumference Around Pulleys
EMERSON Continued				
G	103	7-15/32"	3	7-17/32"
H	104	8-1/64"	59	8-3/16"
J	161	6-55/64"	57	7-3/32"
K	102	6-57/64"	61	6-29/32"
L	103	7-15/32"	3	7-17/32"
LLW	106	7-1/4"	56	7-9/32"
M	118	10-23/64"	18	10-15/32"
P	174	7-3/4"	11	7-29/32"
S	159	8-1/32"	62	8-1/4"
X	118	10-23/64"	18	10-15/32"
Z	103	7-15/32"	3	7-17/32"
A130	104	8-1/64"	59	8-3/16"
A132	104	8-1/64"	59	8-3/16"
A148	104	8-1/64"	59	8-3/16"
AA131	103	7-15/32"	3	7-17/32"
AB178	118	10-23/64"	18	10-15/32"
AB182	118	10-23/64"	18	10-15/32"
AB183	118	10-23/64"	26	10-1/16"
AB184	118	10-23/64"	18	10-15/32"
AC130	104	8-1/64"	59	8-3/16"
AC149	104	8-1/64"	59	8-3/16"
AC168	104	8-1/64"	59	8-3/16"
AC202	104	8-1/64"	59	8-3/16"
AE163	114	8-15/64"	14	8-7/16"
AF171	106	7-1/4"	56	7-9/32"
AF173	106	7-1/4"	56	7-9/32"
AF176	106	7-1/4"	56	7-9/32"
AF179	106	7-1/4"	56	7-9/32"
AF180	106	7-1/4"	56	7-9/32"
AF185	106	7-1/4"	56	7-9/32"
AG151	118	10-23/64"	18	10-15/32"
AH162	106	7-1/4"	56	7-9/32"
AH165	156	7-9/32"	56	7-9/32"
AH166	106	7-1/4"	56	7-9/32"
AH171	106	7-1/4"	56	7-9/32"
AH173	106	7-1/4"	56	7-9/32"
AH174	106	7-1/4"	56	7-9/32"
AH176	106	7-1/4"	56	7-9/32"
AH179	156	7-9/32"	56	7-9/32"
AH180	106	7-1/4"	56	7-9/32"
AH185	106	7-1/4"	56	7-9/32"
AJ130	104	8-1/64"	59	8-3/16"
AJ137	104	8-1/64"	59	8-3/16"
AJ149	104	8-1/64"	59	8-3/16"
AL130	104	8-1/64"	59	8-3/16"
AL132	104	8-1/64"	59	8-3/16"
AL149	104	8-1/64"	59	8-3/16"
AL164	104	8-1/64"	59	8-3/16"
AL168	104	8-1/64"	59	8-3/16"
AL202	104	8-1/64"	5	7-9/16"
ALLW130	156	7-9/32"	56	7-9/32"

Model	G-C Belt	Circumference Around Pulleys	JFD Belt	Circumference Around Pulleys
EMERSON Continued				
ALLW132	156	7-9/32"	56	7-9/32"
ALLW149	156	7-9/32"	56	7-9/32"
ALLW168	156	7-9/32"	56	7-9/32"
AM131	103	7-15/32"	3	7-17/32"
AM153	103	7-15/32"	3	7-17/32"
AM169	103	7-15/32"	3	7-17/32"
AM187	103	7-15/32"	3	7-17/32"
AP165	156	7-9/32"	56	7-9/32"
AP166	156	7-9/32"	56	7-9/32"
AP171	156	7-9/32"	56	7-9/32"
AP173	156	7-9/32"	56	7-9/32"
AP174	156	7-9/32"	56	7-9/32"
AP176	156	7-9/32"	56	7-9/32"
AP177	156	7-9/32"	56	7-9/32"
AP180	156	7-9/32"	56	7-9/32"
AP185	156	7-9/32"	56	7-9/32"
AR165	106	7-1/4"	56	7-9/32"
AR166	106	7-1/4"	56	7-9/32"
AR171	106	7-1/4"	56	7-9/32"
AR173	156	7-9/32"	56	7-9/32"
AR174	106	7-1/4"	56	7-9/32"
AR176	106	7-1/4"	56	7-9/32"
AR177	106	7-1/4"	56	7-9/32"
AR180	106	7-1/4"	56	7-9/32"
AR185	156	7-9/32"	----	
AS179	106	7-1/4"	56	7-9/32"
AV193	155	7-35/64"	3	7-17/32"
AW171	156	7-9/32"	56	7-9/32"
AW173	156	7-9/32"	56	7-9/32"
AW174	156	7-9/32"	56	7-9/32"
AW176	156	7-9/32"	56	7-9/32"
AW180	156	7-9/32"	56	7-9/32"
AW185	156	7-9/32"	56	7-9/32"
B131	103	7-15/32"	3	7-17/32"
BF191	103	7-15/32"	3	7-17/32"
C134	118	10-23/64"	18	10-15/32"
C136	118	10-23/64"	18	10-15/32"
C138	118	10-23/64"	18	10-15/32"
C139	118	10-23/64"	18	10-15/32"
C140	118	10-23/64"	18	10-15/32"
C142	118	10-23/64"	18	10-15/32"
D5	118	10-23/64"	18	10-15/32"
D134	118	10-23/64"	18	10-15/32"
D136	118	10-23/64"	18	10-15/32"
D138	118	10-23/64"	18	10-15/32"
D139	118	10-23/64"	18	10-15/32"
D140	118	10-23/64"	18	10-15/32"
D142	118	10-23/64"	18	10-15/32"
D146	118	10-23/64"	18	10-15/32"
F117	103	7-15/32"	3	7-17/32"
F122	103	7-15/32"	3	7-17/32"

Model	G-C Belt	Circumference Around Pulleys	JFD Belt	Circumference Around Pulleys
EMERSON Continued				
F133	103	7-15/32"	3	7-17/32"
F135	103	7-15/32"	3	7-17/32"
F141	103	7-15/32"	3	7-17/32"
G4	103	7-15/32"	3	7-17/32"
G127	103	7-15/32"	3	7-17/32"
H5	104	8-1/64"	59	8-3/16"
H5L	104	8-1/64"	59	8-3/16"
H130	104	8-1/64"	59	8-3/16"
H137	104	8-1/64"	59	8-3/16"
J106	161	8-55/64"	57	7-3/32"
K106	-----		61	6-29/32"
K116	102	6-57/64"	61	6-29/32"
K121	102	6-57/64"	61	6-29/32"
K123	102	8-57/64"	61	6-29/32"
LAC4	103	7-15/32"	3	7-17/32"
LAC5	103	7-15/32"	3	7-17/32"
L117	103	7-15/32"	3	7-17/32"
L117LW	106	7-1/4"	3	7-17/32"
L122	103	7-15/32"	3	7-17/32"
L122LW	106	7-1/4"	3	7-17/32"
L133	103	7-15/32"	3	7-17/32"
L133LW	106	7-1/4"	3	7-17/32"
L135	103	7-15/32"	3	7-17/32"
L135LW	106	7-1/4"	3	7-17/32"
L137	103	7-15/32"	3	7-17/32"
L141	103	7-15/32"	3	7-17/32"
L141LW	106	7-1/4"	3	7-17/32"
L143	103	7-15/32"	56	7-9/32"
L143W	103	7-15/32"	3	7-17/32"
L150	103	7-15/32"	3	7-17/32"
M134	118	10-23/64"	18	10-15/32"
M136	118	10-23/64"	18	10-15/32"
M139	118	10-23/64"	18	10-15/32"
M140	118	10-23/64"	18	10-15/32"
M142	118	10-23/64"	18	10-15/32"
M146	118	10-23/64"	18	10-15/32"
P117	174	7-3/4"	11	7-29/32"
P135	174	7-3/4"	11	7-29/32"
S7	159	8-1/32"	62	8-1/4"
S50	159	8-1/32"	62	8-1/4"
S134	162	8-13/64"	62	8-1/4"
S138	162	8-13/64"	62	8-1/4"
S139	162	8-13/64"	62	8-1/4"
S140	162	8-13/64"	62	8-1/4"
S147	159	8-1/32"	62	8-1/4"
S151	159	8-1/32"	62	8-1/4"
X146	118	10-23/64"	18	10-15/32"
X175	118	10-23/64"	18	10-15/32"
X178	118	10-23/64"	18	10-15/32"
X183	118	10-23/64"	18	10-15/32"
Z117	103	7-15/32"	3	7-17/32"

Model	G-C Belt	Circumference Around Pulleys	JFD Belt	Circumference Around Pulleys
-------	----------	------------------------------	----------	------------------------------

EMERSON Continued

Z122	103	7-15/32"	3	7-17/32"
Z133	155	7-35/64"	3	7-17/32"
Z135	103	7-15/32"	3	7-17/32"
Z141	103	7-15/32"	3	7-17/32"
Z143	155	7-35/64"	3	7-17/32"
Z150	103	7-15/32"	3	7-17/32"
Z159	103	7-15/32"	3	7-17/32"
Z160	103	7-15/32"	3	7-17/32"

FADA

190	109	8-1/2"	14	8-7/16"
191	109	8-1/2"	14	8-7/16"
192	109	8-1/2"	14	8-7/16"
193	109	8-1/2"	14	8-7/16"
211	130	11-5/64"	37	11-9/32"
212	138	11-57/64"	41	11-15/16"
216	138	11-57/64"	41	11-15/16"
220	130	11-5/64"	30	11-1/4"
270	110	8-25/64"	10	8-1/2"
271	110	8-25/64"	10	8-1/2"
290	130	11-5/64"	37	11-9/32"
291	130	11-5/64"	37	11-9/32"
311	130	11-5/64"	37	11-9/32"
312	138	11-57/64"	41	11-15/16"
316	138	11-57/64"	41	11-15/16"

FAIRBANKS-MORSE

GA	143	11-13/16"	40	12-5/16"
5C	143	11-13/16"	46	13-1/8"
5D	143	11-13/16"	46	13-1/8"
6A	143	11-13/16"	46	13-1/8"
6C	143	11-13/16"	46	13-1/8"
7D	168	12-13/16"	77	12-7/8"
8A	168	12-13/16"	54	12-1/16"
58	173	11-7/16"	32	11-1/16"
72	173	11-7/16"	32	11-1/16"
73	173	11-7/16"	32	11-1/16"
82	109	8-1/2"	9	8-17/32"
90	109	8-1/2"	9	8-17/32"
91	140	12-7/32"	40	12-5/16"
100	109	8-1/2"	9	8-17/32"
110	109	8-1/2"	9	8-17/32"
120	140	12-7/32"	4	8-3/32"

Model	G-C Belt	Circumference Around Pulleys	JFD Belt	Circumference Around Pulleys
GAROD				
370	119	9-17/32"	19	9-13/16"
370A	119	9-17/32"	19	9-13/16"
371	119	9-17/32"	19	9-13/16"
380	124	10-17/64"	52	10-9/16"
381	129	10-41/64"	52	10-9/16"
731	119	9-17/32"	19	9-13/16"
731A	119	9-17/32"	19	9-13/16"
803E	164	10-1/4"	16	9-7/16"
830	119	9-17/32"	52	10-9/16"
830A	119	9-17/32"	52	10-9/16"
831	119	9-17/32"	52	10-9/16"
831A	119	9-17/32"	52	10-9/16"

GAROD - Manual Tuning Models

309	187	15-17/64"	86	15-7/16"
903	187	15-17/64"	86	15-7/16"
930	119	9-17/32"	52	10-9/16"
930A	119	9-17/32"	52	10-9/16"
1203	187	15-17/64"	86	15-7/16"
1204	187	15-17/64"	86	15-7/16"
1240	120	10-45/64"	20	10-11/16"
1240A	120	10-45/64"	20	10-11/16"
1603	187	15-17/64"	86	15-7/16"
1604	187	15-17/64"	86	15-7/16"
1650	120	10-45/64"	20	10-11/16"
1650A	120	10-45/64"	20	10-11/16"
3012	187	15-17/64"	86	15-7/16"
3016	187	15-17/64"	86	15-7/16"
4012	187	15-17/64"	86	15-7/16"
4016	187	15-17/64"	86	15-7/16"
4110	120	10-45/64"	20	10-11/16"
4560	120	10-45/64"	21	10-3/4"
5140	120	10-45/64"	20	10-11/16"
5240	120	10-45/64"	20	10-11/16"
6250	121	10-11/16"	20	10-11/16"
6385	182	15-13/16"	85	15-13/16"

GAROD - Automatic Tuning Models

309	170	16-19/64"	89	16-13/16"
903	170	16-19/64"	89	16-13/16"
1203	170	16-19/64"	89	16-13/16"
1204	170	16-19/64"	89	16-13/16"
1603	170	16-19/64"	89	16-13/16"
1604	170	16-19/64"	89	16-13/16"
3012	170	16-19/64"	89	16-13/16"
3016	170	16-19/64"	89	16-13/16"
4012	170	16-19/64"	89	16-13/16"

Model	G-C Belt	Circumference Around Pulleys	JFD Belt	Circumference Around Pulleys
--------------	---------------------	---	---------------------	---

GAROD - Automatic Tuning Models Continued

4016	170	16-19/64"	89	16-13/16"
------	-----	-----------	----	-----------

GENERAL ELECTRIC

F107	174	7-3/4"	88	7-13/16"
F109	174	7-3/4"	88	7-13/16"
F135	174	7-3/4"	88	7-13/16"

GOODYEAR

1070	126	9-61/64"	19	9-13/16"
1173	153	8-39/64"	14	8-7/16"
1174	107	7-11/16"	5	7-9/16"
112-125	126	9-61/64"	26	10-1/16"
112-176	107	7-11/16"	55	7-11/16"
112-194	153	8-39/64"	12	8-19/32"

GRUNOW

11G	145	12-39/64"	39	12-7/16"
573	131	11-9/64"	30	11-1/4"
631	131	11-9/64"	30	11-1/4"
643	131	11-9/64"	30	11-1/4"
711	131	11-9/64"	30	11-1/4"
723	131	11-9/64"	30	11-1/4"
731	131	11-9/64"	30	11-1/4"
733	131	11-9/64"	30	11-1/4"
735	131	11-9/64"	30	11-1/4"
823	132	10-31/32"	32	11-1/16"
831	132	10-31/32"	32	11-1/16"
833	132	10-31/32"	32	11-1/16"
835	132	10-31/32"	32	11-1/16"
941	132	10-31/32"	32	11-1/16"
1191	145	12-39/64"	39	12-7/16"
1191B	145	12-39/64"	24	10-5/16"
1192	145	12-39/64"	44	12-9/16"
1198	----		39	12-7/16"
1201	149	15-1/64"	48	14-27/32"

HALLICRAFTERS

5PA	117	9-1/16"	17	9-5/32"
5T	117	9-1/16"	76	8-15/16"
S14	119	9-17/32"	63	9-3/8"

Model	G-C Belt	Circumference Around Pulleys	JFD Belt	Circumference Around Pulleys
HOWARD				
450	180	10-27/32"	21	10-3/4"
518	141	11-3/4"	36	11-9/16"
520	141	11-3/4"	36	11-9/16"
565	141	11-3/4"	36	11-9/16"
568	141	11-3/4"	36	11-9/16"
568R	141	11-3/4"	43	11-7/8"
575	141	11-3/4"	36	11-9/16"
580	141	11-3/4"	36	11-9/16"
585	141	11-3/4"	36	11-9/16"
718APC	141	11-3/4"	43	11-7/8"
718C	141	11-3/4"	43	11-7/8"
718FM	141	11-3/4"	43	11-7/8"
C-8 Projector	168	12-13/16"	77	12-7/8"
R-8 Projector	150	15-61/64"	85	15-13/16"

KINGSTON

17447	147	14-27/64"	47	14-1/2"
17514	104	8-1/64"	4	8-3/32"
17628	102	6-57/64"	2	6-13/16"
17676	132	10-31/32"	32	11-1/16"

KNIGHT

11A	169	17-13/32"	68	17-7/16"
11S	179	17-37/64"	81	17-9/16"
16R	179	17-37/64"	81	17-9/16"
16S	169	17-13/32"	68	17-7/16"
A9788	144	12-15/32"	44	12-9/16"
A9789	144	12-15/32"	44	12-9/16"
A9830	126	9-61/64"	26	10-1/16"
A9831	126	9-61/64"	26	10-1/16"
A9852	144	12-15/32"	44	12-9/16"
A9853	144	12-15/32"	44	12-9/16"
A9854	144	12-15/32"	44	12-9/16"
B10510	170	16-19/64"	50	16-7/16"
B10511	170	16-19/64"	50	16-7/16"
B10512	170	16-19/64"	50	16-7/16"
B10515	170	16-19/64"	50	16-7/16"
B10516	170	16-19/64"	50	16-7/16"
B10517	170	16-19/64"	50	16-7/16"
B10518	170	16-19/64"	50	16-7/16"
B10520	179	17-37/64"	68	17-7/16"
B10521	179	17-37/64"	68	17-7/16"
B10522	179	17-37/64"	68	17-7/16"
B10523	179	17-37/64"	68	17-7/16"
B10525	179	17-37/64"	68	17-7/16"
B10526	179	17-37/64"	68	17-7/16"

Model	G-C Belt	Circumference Around Pulleys	JFD Belt	Circumference Around Pulleys
KNIGHT Continued				
B10537	179	17-37/64"	68	17-7/16"
B10538	179	17-37/64"	68	17-7/16"
B10539	179	17-37/64"	68	17-7/16"
B10540	170	16-19/64"	50	16-7/16"
B10541	170	16-19/64"	50	16-7/16"
B10542	170	16-19/64"	50	16-7/16"
B10760	179	17-37/64"	68	17-7/16"
B10761	179	17-37/64"	68	17-7/16"
B10762	179	17-37/64"	68	17-7/16"
B10765	179	17-37/64"	68	17-7/16"
B10766	179	17-37/64"	68	17-7/16"
B10767	179	17-37/64"	68	17-7/16"
B10773	170	16-19/64"	50	16-7/16"
E10744	169	17-13/32"	68	17-7/16"
E10745	169	17-13/32"	68	17-7/16"
E10850	169	17-13/32"	68	17-7/16"
E10851	169	17-13/32"	68	17-7/16"
E10880	169	17-13/32"	68	17-7/16"
E10881	169	17-13/32"	68	17-7/16"
H9791	126	9-61/64"	26	10-1/16"
H9792	126	9-61/64"	26	10-1/16"
H9795	126	9-61/64"	26	10-1/16"

LAFAYETTE

B15	115	9-13/64"	15	9-5/16"
B22	115	9-13/64"	15	9-5/16"
B30	123	9-7/8"	26	10-1/16"
B35	115	9-13/64"	15	9-5/16"
C46	121	10-11/16"	21	10-3/4"
C47	121	10-11/16"	21	10-3/4"
C61	121	10-11/16"	21	10-3/4"
C62	121	10-11/16"	21	10-3/4"
C64	121	10-11/16"	21	10-3/4"
MB3	139	12-9/32"	40	12-5/16"
MB4	139	12-9/32"	40	12-5/16"
MB5	139	12-9/32"	40	12-5/16"
MB6	139	12-9/32"	40	12-5/16"

MAJESTIC - New Type Dial

65	161	6-55/64"	2	6-13/16"
66	161	6-55/64"	2	6-13/16"
75	161	6-55/64"	2	6-13/16"
76	161	6-55/64"	2	6-13/16"
85	161	6-55/64"	2	6-13/16"
86	161	6-55/64"	2	6-13/16"
650	161	6-55/64"	2	6-13/16"
750	161	6-55/64"	2	6-13/16"

Model	G-C Belt	Circumference Around Pulleys	JFD Belt	Circumference Around Pulleys
--------------	-----------------	-------------------------------------	-----------------	-------------------------------------

MAJESTIC - New Type Dial Continued

850	160	8-11/16"	53	8-11/16"
1050	160	8-11/16"	53	8-11/16"
1056	176	22-35/64"	74	22-9/16"
1058	160	8-11/16"	10	8-1/2"
1250	160	8-11/16"	53	8-11/16"
1356	176	22-35/64"	74	22-9/16"
1656	176	22-35/64"	74	22-9/16"

MAJESTIC - Old Type Dial

65	177	7-13/32"	6	7-13/32"
66	177	7-13/32"	6	7-13/32"
75	177	7-13/32"	6	7-13/32"
76	177	7-13/32"	6	7-13/32"
85	177	7-13/32"	6	7-13/32"
86	177	7-13/32"	6	7-13/32"
650	177	7-13/32"	6	7-13/32"
750	177	7-13/32"	6	7-13/32"
850	109	8-1/2"	12	8-19/32"
1050	109	8-1/2"	12	8-19/32"
1056	175	21-5/16"	73	21-1/16"
1058	175	21-5/16"	73	21-1/16"
1250	109	8-1/2"	12	8-19/32"
1356	175	21-5/16"	73	21-1/16"
1656	175	21-5/16"	73	21-1/16"
7182	106	7-1/4"	56	7-9/32"

MAJESTIC - With Pully Idler

1056	176	22-35/64"	74	22-9/16"
1058	176	22-35/64"	74	22-9/16"
1356	176	22-35/64"	74	22-9/16"
1656	176	22-35/64"	74	22-9/16"
17182	160	8-11/16"	60	8-3/4"
17203	161	6-55/64"	61	6-29/32"

McMURDO SILVER

All models	117	9-1/16"	76	8-15/16"
------------	-----	---------	----	----------

NORTH ELECT.

Type One	117	9-1/16"	17	9-5/32"
Other Nos.	152	10-1/2"	52	10-9/16"

Model	G-C Belt	Circumference Around Pulleys	JFD Belt	Circumference Around Pulleys
PHILCO				
54-7194	-----		20	10-11/16"
R.C.A.				
5Q1	111	7-15/16"	11	7-29/32"
5Q2	111	7-15/16"	11	7-29/32"
5Q4	111	7-15/16"	11	7-29/32"
5Q2X	111	7-15/16"	11	7-29/32"
85BK	131	11-9/64"	33	11-5/32"
85BT	131	11-9/64"	33	11-5/32"
85BT6	177	7-13/32"	6	7-13/32"
85E	122	10-3/8"	22	10-1/2"
85K	177	7-13/32"	6	7-13/32"
85K1	126	9-61/64"	23	10-1/3"
85T	112	8-43/64"	12	8-19/32"
85T1	177	7-13/32"	6	7-13/32"
85T2	113	8-3/32"	13	8-5/8"
85T5	111	7-15/16"	11	7-29/32"
85T8	111	7-15/16"	11	7-29/32"
85T9	126	9-61/64"	23	10-1/3"
86BK	131	11-9/64"	33	11-5/32"
86BT	131	11-9/64"	33	11-5/32"
86E	140	12-7/32"	42	12-5/16"
86K	140	12-7/32"	42	12-5/16"
86K2	111	7-51/64"	11	7-29/32"
86K7	140	12-7/32"	42	12-5/16"
86T	131	11-9/64"	33	11-5/32"
86T1	131	11-9/64"	33	11-5/32"
86T2	111	7-15/16"	11	7-29/32"
86T3	111	7-15/16"	11	7-29/32"
86T4	131	11-9/64"	33	11-5/32"
86T44	131	11-9/64"	33	11-5/32"
86T6	111	7-15/16"	11	7-29/32"
86X	177	7-13/32"	6	7-13/32"
86X4	177	7-13/32"	6	7-13/32"
87EY	131	11-9/64"	33	11-5/32"
87K	140	12-7/32"	42	12-5/16"
87K1	140	12-7/32"	42	12-5/16"
87K2	140	12-7/32"	42	12-5/16"
87T	131	11-9/64"	33	11-5/32"
87T1	111	7-15/16"	11	7-29/32"
87T2	140	12-7/32"	42	12-5/16"
87T7	111	7-15/16"	88	7-13/16"
87X	131	11-9/64"	33	11-5/32"
87Y	131	11-9/64"	33	11-5/32"
88K	140	12-7/32"	42	12-5/16"
88W	140	12-7/32"	42	12-5/16"
88U	140	12-7/32"	42	12-5/16"
88U2	140	12-7/32"	42	12-5/16"
95FT	111	7-15/16"	88	7-13/16"

Model	G-C Belt	Circumference Around Pulleys	JFD Belt	Circumference Around Pulleys
R.C.A. Continued				
ACR111	116	9-5/16"	17	9-5/32"
U101	177	7-13/32"	6	7-13/32"
U102E	122	10-3/8"	22	10-1/2"
U103	177	7-13/32"	6	7-13/32"
U105	140	12-7/32"	42	12-5/16"
U106	140	12-7/32"	42	12-5/16"
U107	140	12-7/32"	42	12-5/16"
U813	140	12-7/32"	42	12-5/16"
153 Osc.	140	12-7/32"	78	12-1/32"
325C	-----		88	7-13/16"
501	-----		88	7-13/16"
502	-----		88	7-13/16"
502X	-----		88	7-13/16"
504	-----		88	7-13/16"
810K	140	12-7/32"	42	12-5/16"
810K1	140	12-7/32"	42	12-5/16"
810T	140	12-7/32"	42	12-5/16"
810T4	140	12-7/32"	42	12-5/16"
812X	138	11-57/64"	43	11-7/8"
RC278A	112	8-43/64"	11	7-29/32"
RC289A	131	11-9/64"	33	11-5/32"
RC290A	140	12-7/32"	42	12-5/16"
RC294	112	8-43/64"	6	7-13/32"
RC294B	112	8-43/64"	12	8-19/32"
RC314	122	10-3/8"	22	10-1/2"
RC314C	113	8-3/32"	13	8-5/8"
RC315B	111	7-15/16"	88	7-13/16"
RC315C	111	7-15/16"	88	7-13/16"
RC319B	140	12-7/32"	78	12-1/32"
RC325	111	7-15/16"	23	10-1/3"
RC325C	111	7-15/16"	11	7-29/32"
RC325D	111	7-15/16"	11	7-29/32"
RC326	151	14-57/64"	48	14-27/32"
RC327	184	16-27/64"	50	16-7/16"
RC328	141	11-3/4"	43	11-7/8"
RC366	111	7-15/16"	88	7-13/16"
30461	129	10-41/64"	22	10-1/2"
31527	115	9-13/64"	15	9-5/16"

RADIO PRODUCTS

10305 *CD	154	11-47/64"	78	12-1/32"
11117 *CD	144	12-15/32"	39	12-7/16"
13755 *CD	190	17-5/8"	81	17-9/16"
13762 *CD	191	22-49/64"	74	22-9/16"

Model	G-C Belt	Circumference Around Pulleys	JFD Belt	Circumference Around Pulleys
--------------	-----------------	-------------------------------------	-----------------	-------------------------------------

SCOTT

Type One	119	19-17/32"	90	19-9/16"
Type Two	152	10-1/2"	24	10-5/16"

SILVERTONE (Sears Roebuck)

1930	114	8-15/64"	14	8-7/16"
1940	114	8-15/64"	14	8-7/16"
1941	145	12-39/64"	45	12-11/16"
1956	114	8-15/64"	14	8-7/16"
1970	114	8-15/64"	14	8-7/16"
1970A	114	8-15/64"	14	8-7/16"
1978	-----		14	8-7/16"
1981	145	12-39/64"	45	12-11/16"
1981C	145	12-39/64"	45	12-11/16"
7170	145	12-39/64"	45	12-11/16"
7170A	145	12-39/64"	45	12-11/16"
7221	115	9-13/64"	76	8-15/16"
7340	145	12-39/64"	45	12-11/16"
12645	115	9-13/64"	80	9-3/16"

SILVER MARSHALL

846	130	11-5/64"	30	11-1/4"
1731	130	11-5/64"	30	11-1/4"

SIMPLEX

8J	108	8-21/32"	17	9-5/32"
W	108	8-21/32"	8	8-9/16"

SONORA

11S	169	17-13/32"	68	17-7/16"
16R	169	17-13/32"	68	17-7/16"

SPARTON

517	147	14-27/64"	47	14-1/2"
517B	147	14-27/64"	47	14-1/2"
517W	147	14-27/64"	47	14-1/2"
517X	145	12-39/64"	39	12-7/16"
518	146	13-3/16"	46	13-1/8"
518X	146	13-3/16"	46	13-1/8"
527-2	146	13-3/16"	46	13-1/8"
528-2	146	13-3/16"	46	13-1/8"

Model	G-C Belt	Circumference Around Pulleys	JFD Belt	Circumference Around Pulleys
-------	----------	------------------------------	----------	------------------------------

SPARTON Continued

537	146	13-3/16"	46	13-1/8"
538	146	13-3/16"	46	13-1/8"
538X	146	13-3/16"	46	13-1/8"
547X	146	13-3/16"	46	13-1/8"
548X	146	13-3/16"	46	13-1/8"
557	147	14-27/64"	47	14-1/2"
558	146	13-3/16"	75	12-15/16"
558B	146	13-3/16"	46	13-1/8"
558BX	146	13-3/16"	46	13-1/8"
558C	146	13-3/16"	46	13-1/8"
558CX	146	13-3/16"	46	13-1/8"
558X	-----		46	13-1/8"
567	147	14-27/64"	47	14-1/2"
568	146	13-3/16"	46	13-1/8"
568X	146	13-3/16"	46	13-1/8"
577	146	13-3/16"	46	13-1/8"
578	146	13-3/16"	46	13-1/8"
578X	146	13-3/16"	46	13-1/8"
587-2	146	13-3/16"	46	13-1/8"
588-2	146	13-3/16"	46	13-1/8"
617	146	13-3/16"	46	13-1/8"
628	146	13-3/16"	46	13-1/8"
628X	146	13-3/16"	46	13-1/8"
637-6	146	13-3/16"	46	13-1/8"
638-6	146	13-3/16"	46	13-1/8"
667	146	13-3/16"	46	13-1/8"
668	146	13-3/16"	46	13-1/8"
668X	146	13-3/16"	46	13-1/8"
678	146	13-3/16"	46	13-1/8"
678A	146	13-3/16"	46	13-1/8"
678X	146	13-3/16"	46	13-1/8"
687-6	146	13-3/16"	46	13-1/8"
688-6	146	13-3/16"	46	13-1/8"
727X	134	11-2/8"	34	11-1/2"
727XD	134	11-3/8"	34	11-1/2"
728X	134	11-3/8"	34	11-1/2"
748X	146	13-13/16"	46	13-1/8"
768	134	11-3/8"	34	11-1/2"
778	134	11-3/8"	34	11-1/2"
827X	134	11-3/8"	34	11-1/2"
827XD	134	11-3/8"	34	11-1/2"
867	134	11-3/8"	34	11-1/2"
877X	134	11-3/8"	34	11-1/2"
928X	134	11-3/8"	34	11-1/2"
968	134	11-3/8"	34	11-1/2"
987	134	11-3/8"	34	11-1/2"
997X	134	11-3/8"	34	11-1/2"
1068	134	11-3/8"	34	11-1/2"
1068X	134	11-3/8"	71	11-3/16"
1078	134	11-3/8"	34	11-1/2"
1078X	134	11-3/8"	71	11-3/16"

Model	G-C Belt	Circumference Around Pulleys	JFD Belt	Circumference Around Pulleys
-------	----------	------------------------------	----------	------------------------------

SPARTON Continued

1084	120	10-45/64"	52	10-9/16"
1167	134	11-3/8"	34	11-1/2"
1268	134	11-3/8"	34	11-1/2"
1288P	134	11-3/8"	34	11-1/2"
1288LXP	134	11-3/8"	34	11-1/2"
1567	134	11-3/8"	34	11-1/2"
1568	134	11-3/8"	34	11-1/2"
1867	134	11-3/8"	34	11-1/2"

STROMBERG CARLSON

All models	151	14-57/64"	48	14-27/32"
------------	-----	-----------	----	-----------

TRUETONE

D-692	135	11"	29	10-13/16"
D-694	135	11"	29	10-13/16"
D-692 late	194	11-21/32"	34	11-1/2"

ULTRAMAR

66A	131	11-9/64"	71	11-3/16"
96	131	11-9/64"	71	11-3/16"
96A	131	11-9/64"	71	11-3/16"
120	127	9-59/64"	26	10-1/16"
801	127	9-59/64"	26	10-1/16"
802	127	9-59/64"	26	10-1/16"

WELLS-GARDNER

2C	164	10-1/4"	64	10-3/16"
2D	192	Straight belt	82	18-9/16"
6F	164	10-1/4"	64	10-3/16"
7G	163	9-19/64"	63	9-3/8"
9C	163	9-19/64"	63	9-3/8"
14	131W	11-9/32"	35	11-3/32"
15	131W	11-9/32"	35	11-3/32"
16	131W	11-9/32"	35	11-3/32"
17B2	131W	11-9/32"	31	11-5/16"
17L	192	Straight belt	82	18-9/16"
17P4	131W	11-9/32"	31	11-5/16"
17T1	131W	11-9/32"	31	11-5/16"
27L	193	Straight belt	83	14-9/16"
57E	168	12-13/16"	46	13-1/8"
57F	-----		64	10-3/16"
A1	131W	11-9/32"	35	11-3/32"

Model	G-C Belt	Circumference Around Pulleys	JFD Belt	Circumference Around Pulleys
--------------	-----------------	-------------------------------------	-----------------	-------------------------------------

WELLS-GARDNER Continued

A2	131W	11-9/32"	35	11-3/32"
A3	131W	11-9/32"	35	11-3/32"
A4	131W	11-9/32"	35	11-3/32"
A5	131W	11-9/32"	35	11-3/32"
OD	163	9-19/64"	17	9-5/32"
OE	192	Straight belt	82	18-9/16"
88A9	170	16-19/64"	50	16-7/16"
8X35	163	9-19/64"	63	9-3/8"
8X36	164	10-1/4"	64	10-3/16"
8X42	192	Straight belt	82	18-9/16"
8X46	193	Straight belt	83	14-9/16"
8X47	168	12-13/16"	81	17-9/16"
8X57	131W	11-9/32"	31	11-5/16"
8X62	170	16-19/64"	70	16-15/32"

WESTINGHOUSE

1029X	124	10-17/64"	24	10-5/16"
1029Y	124	10-17/64"	24	10-5/16"
1230X	124	10-17/64"	24	10-5/16"
1230Y	124	10-17/64"	24	10-5/16"

WILCOX-GAY

6S12	125	10-25/64"	25	10-15/32"
A21	125	10-25/64"	25	10-15/32"

ZENITH

5F134	117	9-1/16"	80	9-3/16"
5F166	117	9-1/16"	80	9-3/16"
5F233	167	8-13/16"	84	8-13/16"
5F251	167	8-13/16"	84	8-13/16"
5S29	101	6-23/32"	2	6-13/16"
5S29A	101	6-23/32"	2	6-13/16"
5S56	101	6-23/32"	2	6-13/16"
5S56A	101	6-23/32"	1	6-5/8"
5S119	117	9-1/16"	80	9-3/16"
5S126	117	9-1/16"	80	9-3/16"
5S127	117	9-1/16"	80	9-3/16"
5S150	117	9-1/16"	80	9-3/16"
5S151	117	9-1/16"	80	9-3/16"
5S161	117	9-1/16"	80	9-3/16"
5S233	167	8-13/16"	84	8-13/16"
5S251	167	8-13/16"	84	8-13/16"
5X230	167	8-13/16"	84	8-13/16"
5X248	167	8-13/16"	84	8-13/16"
5X274	167	8-13/16"	84	8-13/16"

Model	G-C Belt	Circumference Around Pulleys	JFD Belt	Circumference Around Pulleys
ZENITH Continued				
6B107	168	12-13/16"	46	13-1/8"
6B129	168	12-13/16"	46	13-1/8"
6B164	168	12-13/16"	46	13-1/8"
6J230	167	8-13/16"	13	8-5/8"
6J257	167	8-13/16"	13	8-5/8"
6J436	117	9-1/16"	80	9-3/16"
6J463	117	9-1/16"	80	9-3/16"
6S27	116	9-5/16"	16	9-7/16"
6S27A	116	9-5/16"	16	9-7/16"
6S29	116	9-5/16"	15	9-5/16"
6S52	116	9-5/16"	16	9-7/16"
6S52A	116	9-5/16"	16	9-7/16"
6S128	168	12-13/16"	75	12-15/16"
6S137	168	12-13/16"	75	12-15/16"
6S147	168	12-13/16"	75	12-15/16"
6S152	168	12-13/16"	75	12-15/16"
6S157	168	12-13/16"	75	12-15/16"
6S203	167	8-13/16"	84	8-13/16"
6S222	167	8-13/16"	84	8-13/16"
6S223	167	8-13/16"	84	8-13/16"
6S229	167	8-13/16"	84	8-13/16"
6S238	167	8-13/16"	84	8-13/16"
6S239	167	8-13/16"	84	8-13/16"
6S241	167	8-13/16"	84	8-13/16"
6S249	138	11-57/64"	38	12"
6S254	133	10-61/64"	79	11"
6S256	133	10-61/64"	79	11"
6S330	167	8-13/16"	13	8-5/8"
6S341	133	10-61/64"	21	10-3/4"
63361	167	8-13/16"	13	8-5/8"
6S362	133	10-61/64"	21	10-3/4"
6V27	116	9-5/16"	16	9-7/16"
6V62	116	9-5/16"	16	9-7/16"
7D119	117	9-1/16"	80	9-3/16"
7D126	117	9-1/16"	80	9-3/16"
7D127	117	9-1/16"	80	9-3/16"
7D138	117	9-1/16"	80	9-3/16"
7D148	117	9-1/16"	80	9-3/16"
7D151	117	9-1/16"	80	9-3/16"
7D153	117	9-1/16"	17	9-5/32"
7D162	117	9-1/16"	80	9-3/16"
7D168	117	9-1/16"	17	9-5/32"
7D178	115	9-13/64"	80	9-3/16"
7D203	167	8-13/16"	84	8-13/16"
7D222	167	8-13/16"	84	8-13/16"
7D223	167	8-13/16"	84	8-13/16"
7D229	167	8-13/16"	84	8-13/16"
7D239	167	8-13/16"	84	8-13/16"
7D241	167	8-13/16"	84	8-13/16"
7D243	167	8-13/16"	84	8-13/16"
7D253	167	8-13/16"	84	8-13/16"

Model	G-C Belt	Circumference Around Pulleys	JFD Belt	Circumference Around Pulleys
ZENITH Continued				
7J232	168	12-13/16"	44	12-9/16"
7J259	168	12-13/16"	44	12-9/16"
7J323	138	11-57/64"	36	11-9/16"
7J368	138	11-57/64"	36	11-9/16"
7S28	128	10-19/64"	64	10-3/16"
7S30	128	10-19/64"	28	10-13/32"
7S53 *D	128	10-19/64"	64	10-3/16"
7S53 *C	126	9-61/64"	26	10-1/16"
7S204 *D	168	12-13/16"	77	12-7/8"
7S204 *C	115	9-13/64"	80	9-3/16"
7S232 *D	168	12-13/16"	77	12-7/8"
7S232 *C	115	9-13/64"	80	9-3/16"
7S240 *D	168	12-13/16"	77	12-7/8"
7S240 *C	115	9-13/64"	80	9-3/16"
7S242 *D	168	12-13/16"	77	12-7/8"
7S242 *C	115	9-13/64"	80	9-3/16"
7S258 *D	168	12-13/16"	77	12-7/8"
7S258 *C	115	9-13/64"	80	9-3/16"
7S260 *D	160	12-13/16"	77	12-7/8"
7S260 *C	115	9-13/64"	80	9-3/16"
7S261 *D	168	12-13/16"	77	12-7/8"
7S261 *C	115	9-13/64"	80	9-3/16"
7S363	115	9-13/64"	80	9-3/16"
8S30	146	13-3/16"	46	13-1/8"
8S129	168	12-13/16"	75	12-15/16"
8S154	168	12-13/16"	75	12-15/16"
8S443	117	9-1/16"	80	9-3/16"
8S451	117	9-1/16"	80	9-3/16"
8S463	117	9-1/16"	80	9-3/16"
8S548	115	9-13/64"	80	9-3/16"
8S563	115	9-13/64"	80	9-3/16"
8S586	115	9-13/64"	80	9-3/16"
8S587	115	9-13/64"	80	9-3/16"
8S588	115	9-13/64"	80	9-3/16"
8S647	117	9-1/16"	17	9-5/32"
8S661	117	9-1/16"	17	9-5/32"
9S30	128	10-19/64"	64	10-3/16"
9S54	128	10-19/64"	64	10-3/16"
9S55	128	10-19/64"	64	10-3/16"
9S203 *D	168	12-13/16"	77	12-7/8"
9S203 *C	138	11-57/64"	38	12"
9S203 *M	117	9-1/16"	80	9-3/16"
9S204 *D	168	12-13/16"	77	12-7/8"
9S204 *C	138	11-57/64"	38	12"
9S204 *M	117	9-1/16"	80	9-3/16"
9S222 *D	168	12-13/16"	77	12-7/8"
9S222 *C	138	11-57/64"	38	12"
9S222 *M	117	9-1/16"	17	9-5/32"
9S232 *D	168	12-13/16"	77	12-7/8"
9S232 *C	138	11-57/64"	38	12"
9S232 *M	117	9-1/16"	80	9-3/16"

Model	G-C Belt	Circumference Around Pulleys	JFD Belt	Circumference Around Pulleys
ZENITH Continued				
9S242 *D	168	12-13/16"	77	12-7/8"
9S242 *C	138	11-57/64"	38	12"
9S242 *M	117	9-1/16"	80	9-3/16"
9S244 *D	168	12-13/16"	77	12-7/8"
9S244 *C	138	11-57/64"	38	12"
9S244 *M	117	9-1/16"	80	9-3/16"
9S262 *D	168	12-13/16"	77	12-7/8"
9S262 *C	138	11-57/64"	38	12"
9S262 *M	117	9-1/16"	80	9-3/16"
9S263 *D	168	12-13/16"	77	12-7/8"
9S263 *C	138	11-57/64"	38	12"
9S263 *M	117	9-1/16"	80	9-3/16"
9S264 *D	168	12-13/16"	77	12-7/8"
9S264 *C	138	11-57/64"	38	12"
9S264 *M	117	9-1/16"	80	9-3/16"
9S307	138	11-57/64"	36	11-9/16"
9S324	138	11-57/64"	36	11-9/16"
9S344	138	11-57/64"	36	11-9/16"
9S365 *D	138	11-57/64"	38	12"
9S365 *M	117	9-1/16"	17	9-5/32"
9S367	138	11-57/64"	36	11-9/16"
9S369	138	11-57/64"	36	11-9/16"
10H551	117	9-1/16"	17	9-5/32"
10H571	117	9-1/16"	80	9-3/16"
10S130	168	12-13/16"	75	12-15/16"
10S147	168	12-13/16"	75	12-15/16"
10S153	168	12-13/16"	75	12-15/16"
10S155	168	12-13/16"	75	12-15/16"
10S156	168	12-13/16"	75	12-15/16"
10S157	168	12-13/16"	75	12-15/16"
10S160	168	12-13/16"	75	12-15/16"
10S443	117	9-1/16"	80	9-3/16"
10S452	117	9-1/16"	80	9-3/16"
10S464	117	9-1/16"	80	9-3/16"
10S470	117	9-1/16"	80	9-3/16"
10S491	117	9-1/16"	80	9-3/16"
10S492	117	9-1/16"	80	9-3/16"
10S589	-----		80	9-3/16"
10S590	-----		80	9-3/16"
10S668	117	9-1/16"	17	9-5/32"
10S669	117	9-1/16"	17	9-5/32"
10S690	117	9-1/16"	17	9-5/32"
11S474	117	9-1/16"	80	9-3/16"
12A57	139	12-9/32"	40	12-5/16"
12A58	139	12-9/32"	40	12-5/16"
12H650	117	9-1/16"	17	9-5/32"
12H670	117	9-1/16"	17	9-5/32"
12H671	117	9-1/16"	17	9-5/32"
12H678	117	9-1/16"	17	9-5/32"
12H679	117	9-1/16"	17	9-5/32"
12H689	138	11-57/64"	38	12"

Model	G-C Belt	Circumference Around Pulleys	JFD Belt	Circumference Around Pulleys
ZENITH Continued				
12H695	138	11-57/64"	38	12"
12H696	138	11-57/64"	38	12"
12L57	139	12-9/32"	40	12-5/16"
12L58	139	12-9/32"	40	12-5/16"
12S205 *D	168	12-13/16"	77	12-7/8"
12S205 *C	138	11-57/64"	38	12"
12S205 *M	117	9-1/16"	80	9-3/16"
12S232 *D	168	12-13/16"	77	12-7/8"
12S232 *C	138	11-57/64"	38	12"
12S232 *M	117	9-1/16"	80	9-3/16"
12S245 *D	168	12-13/16"	77	12-7/8"
12S245 *C	138	11-57/64"	38	12"
12S245 *M	117	9-1/16"	80	9-3/16"
12S265 *D	168	12-13/16"	77	12-7/8"
12S265 *C	138	11-57/64"	38	12"
12S265 *M	117	9-1/16"	80	9-3/16"
12S266 *D	168	12-13/16"	77	12-7/8"
12S266 *C	138	11-57/64"	38	12"
12S266 *M	117	9-1/16"	80	9-3/16"
12S267 *D	168	12-13/16"	77	12-7/8"
12S267 *C	138	11-57/64"	38	12"
12S267 *M	117	9-1/16"	80	9-3/16"
12S268 *D	168	12-13/16"	77	12-7/8"
12S268 *C	138	11-57/64"	38	12"
12S268 *M	117	9-1/16"	80	9-3/16"
12S345	138	11-57/64"	36	11-9/16"
12S370	138	11-57/64"	36	11-9/16"
12S371	138	11-57/64"	36	11-9/16"
12S445	138	11-57/64"	38	12"
12S453	138	11-57/64"	38	12"
12S471	138	11-57/64"	38	12"
12S475	138	11-57/64"	38	12"
12S494	138	11-57/64"	38	12"
12S550	-----		38	12"
12S550Z	138	11-57/64"	38	12"
12S568	-----		38	12"
12S568E	138	11-57/64"	38	12"
12S568Z	138	11-57/64"	38	12"
12S569	-----		38	12"
12S569E	138	11-57/64"	38	12"
12S569Z	138	11-57/64"	38	12"
12S595	-----		38	12"
12S595Z	138	11-57/64"	38	12"
12U158	149	15-1/64"	48	14-27/32"
12U159	149	15-1/64"	48	14-27/32"
15S308 *D	138	11-57/64"	38	12"
15S308 *M	117	9-1/16"	17	9-5/32"
15S346 *D	138	11-57/64"	38	12"
15S346 *M	117	9-1/16"	17	9-5/32"
15S372 *D	138	11-57/64"	38	12"
15S372 *M	117	9-1/16"	17	9-5/32"

Model	G-C Belt	Circumference Around Pulleys	JFD Belt	Circumference Around Pulleys
ZENITH Continued				
15S373 *D	138	11-57/64"	38	12"
15S373 *M	117	9-1/16"	17	9-5/32"
15S479 *D	138	11-57/64"	38	12"
15S479 *M	117	9-1/16"	80	9-3/16"
15S495 *D	138	11-57/64"	38	12"
15S495 *M	117	9-1/16"	80	9-3/16"
15U246 *D	168	12-13/16"	77	12-7/8"
15U246 *C	138	11-57/64"	38	12"
15U246 *M	117	9-1/16"	80	9-3/16"
15U269 *D	168	12-13/16"	77	12-7/8"
15U269 *C	138	11-57/64"	38	12"
15U269 *M	117	9-1/16"	80	9-3/16"
15U270 *D	168	12-13/16"	77	12-7/8"
15U270 *C	138	11-57/64"	38	12"
15U270 *M	117	9-1/16"	80	9-3/16"
15U271 *D	168	12-13/16"	77	12-7/8"
15U271 *C	138	11-57/64"	38	12"
15U271 *M	117	9-1/16"	80	9-3/16"
15U272 *D	168	12-13/16"	77	12-7/8"
15U272 *C	138	11-57/64"	38	12"
15U272 *M	117	9-1/16"	80	9-3/16"
15U273 *D	168	12-13/16"	77	12-7/8"
15U273 *C	138	11-57/64"	38	12"
150273 *M	117	9-1/16"	80	9-3/16"
16 Tube				
Stratosphere	139	12-9/32"	54	12-1/16"
16A61	139	12-9/32"	54	12-1/16"
16A63	139	12-9/32"	54	12-1/16"
601	101	6-23/32"	1	6-5/8"
835	160	8-11/16"	53	8-11/16"
880	160	8-11/16"	53	8-11/16"
881	160	8-11/16"	53	8-11/16"
885	160	8-11/16"	53	8-11/16"
901	129	10-41/64"	----	
908	101	6-23/32"	2	6-13/16"
S908	101	6-23/32"	2	6-13/16"
909	101	6-23/32"	2	6-13/16"
S909	101	6-23/32"	2	6-13/16"
935	160	8-11/16"	53	8-11/16"
945	101	6-23/32"	2	6-13/16"
950	101	6-23/32"	2	6-13/16"
960	101	6-23/32"	1	6-5/8"
961	101	6-23/32"	2	6-13/16"
S961	101	6-23/32"	2	6-13/16"
970	128	10-19/64"	64	10-3/16"
975	128	10-19/64"	64	10-3/16"
978	160	8-11/16"	53	8-11/16"
980	160	8-11/16"	53	8-11/16"
983	160	8-11/16"	53	8-11/16"
985	160	8-11/16"	53	8-11/16"
990	160	8-11/16"	53	8-11/16"

Model	G-C Belt	Circumference Around Pulleys	JFD Belt	Circumference Around Pulleys
-------	----------	------------------------------	----------	------------------------------

ZENITH Continued

1000Z 25 Tube Stratosphere	149	15-1/64"	49	15-5/32"
	149	15-1/64"	49	15-5/32"

ZENITH Chassis Numbers

8A01	115	9-13/64"	80	9-3/16"
8A02	115	9-13/64"	80	9-3/16"
8A03	115	9-13/64"	80	9-3/16"
8B01	117	9-1/16"	17	9-5/32"
10A1	115	9-13/64"	80	9-3/16"
10A2	115	9-13/64"	80	9-3/16"
10A3	115	9-13/64"	80	9-3/16"
10B1	117	9-1/16"	17	9-5/32"
10B2	117	9-1/16"	17	9-5/32"
12A1	138	11-57/64"	38	12"
12A2	138	11-57/64"	38	12"
12A3	138	11-57/64"	38	12"
12A4	138	11-57/64"	38	12"
12A6	117	9-1/16"	17	9-5/32"
12B1	117	9-1/16"	17	9-5/32"
12B2	138	11-57/64"	38	12"
14B1	138	11-57/64"	38	12"
1001	160	8-11/16"	53	8-11/16"
1004	168	12-13/16"	75	12-15/16"
1005	117	9-1/16"	80	9-3/16"
1029Y	164	10-1/4"	24	10-5/16"
1101	160	8-11/16"	53	8-11/16"
1103	117	9-1/16"	80	9-3/16"
1105	160	8-11/16"	53	8-11/16"
1117	101	6-23/32"	2	6-13/16"
1167	101	6-23/32"	2	6-13/16"
S1167	101	6-23/32"	2	6-13/16"
1201 *D	160	8-11/16"	53	8-11/16"
1201	160	8-11/16"	10	8-1/2"
1201A *D	160	8-11/16"	53	8-11/16"
1201A	160	8-11/16"	10	8-1/2"
1202	139	12-9/32"	40	12-5/16"
1202A	139	12-9/32"	40	12-5/16"
1203	149	15-1/64"	48	14-27/32"
1204 *D	168	12-13/16"	77	12-7/8"
1204 *C	138	11-57/64"	38	12"
1204 *M	117	9-1/16"	17	9-5/32"
1206	138	11-57/64"	38	12"
1207 *D	138	11-57/64"	38	12"
1207	138	11-57/64"	36	11-9/16"
1501 *D	168	12-13/16"	77	12-7/8"
1501 *C	138	11-57/64"	38	12"
1501 *M	117	9-1/16"	17	9-5/32"
1502 *D	136	11-57/64"	38	12"
1502 *M	117	9-1/16"	17	9-5/32"

Model	G-C Belt	Circumference Around Pulleys	JFD Belt	Circumference Around Pulleys
-------	----------	------------------------------	----------	------------------------------

ZENITH Chassis Numbers Continued

1502A *D	138	11-57/64"	38	12"
1502A *M	117	9-1/16"	17	9-5/32"
1503 *D	138	11-57/64"	38	12"
1503 *M	117	9-1/16"	80	9-3/16"
1601C	139	12-9/32"	54	12-1/16"
1601P	139	12-9/32"	54	12-1/16"
22B1	138	11-57/64"	38	12"
2501	149	15-1/64"	49	15-5/32"
2501C	149	15-1/64"	49	15-5/32"
2501P	149	15-1/64"	49	15-5/32"
5508	101	6-23/32"	2	6-13/16"
5513	101	6-23/32"	2	6-13/16"
5513A	101	6-23/32"	2	6-13/16"
5516	117	9-1/16"	80	9-3/16"
5518	117	9-1/16"	80	9-3/16"
5522	167	8-13/16"	84	8-13/16"
5523	167	8-13/16"	84	8-13/16"
5614	101	6-23/32"	2	6-13/16"
5618	101	6-23/32"	2	6-13/16"
5619	116	9-5/16"	16	9-7/16"
5619A	116	9-5/16"	15	9-5/16"
5621	116	9-5/16"	80	9-3/16"
5627	116	9-5/16"	16	9-7/16"
5634	168	12-13/16"	75	12-15/16"
5635	168	12-13/16"	46	13-1/8"
5638	167	8-13/16"	84	8-13/16"
5642	167	8-13/16"	13	8-5/8"
5644	133	10-61/64"	79	11"
5648	167	8-13/16"	13	8-5/8"
5649	133	10-61/64"	79	11"
5679 *D	117	9-1/16"	80	9-3/16"
5679	117	9-1/16"	84	8-13/16"
5704	128	10-19/64"	64	10-3/16"
5704A	128	10-19/64"	28	10-13/32"
5707	117	9-1/16"	80	9-3/16"
5709 *D	168	12-13/16"	77	12-7/8"
5709	168	12-13/16"	80	9-3/16"
5710	167	8-13/16"	84	8-13/16"
5711	168	12-13/16"	44	12-9/16"
5715	138	11-57/64"	36	11-9/16"
5801	168	12-13/16"	75	12-15/16"
5808	117	9-1/16"	80	9-3/16"
5902	128	10-19/64"	64	10-3/16"
5903	128	10-19/64"	64	10-3/16"
5903A	128	10-19/64"	28	10-13/32"
5905 *D	168	12-13/16"	77	12-7/8"
5905 *C	138	11-57/64"	38	12"
5905 *M	117	9-1/16"	17	9-5/32"
5906 *D	138	11-57/64"	38	12"
5906 *M	117	9-1/16"	17	9-5/32"
5907	138	11-57/64"	36	11-9/16"

Model	G-C Belt	Circumference Around Pulleys	JFD Belt	Circumference Around Pulleys
--------------	---------------------	---	---------------------	---

ZENITH Chassis Numbers Continued

S9061	-----		2	6-13/16"
-------	-------	--	---	----------

ZEPHYR

8J	162	8-13/64"	59	8-3/16"
8JM	162	8-13/64"	59	8-3/16"

G-C Belt Specifications

Belt Interchange Chart G-C To Other Makes

G-C Belt	Other Belt	G-C Belt	Other Belt	G-C Belt	Other Belt
101	1	132	32	163	63
102	2	133	79	164	24
103	3	134	31	165	89
104	4	135	35	166	90
105	5	136	36	167	76
106	56	137	37	168	77
107	7	138	38	169	68
108	8	139	40	170	50
109	9	140	42	171	71
110	53	141	43	172	72
111	88	142	54	173	34
112	12	143	43	174	88
113	4	144	44	175	73
114	59	145	45	176	74
115	15	146	46	177	6
116	16	147	47	178	39
117	17	148	83	179	81
118	18	149	49	180	29
119	----	150	85	181	82
120	20	151	48	182	85
121	21	152	52	183	86
122	22	153	53	184	51
123	19	154	54	185	----
124	24	155	3	186	----
125	25	156	56	187	----
126	26	157	57	188	----
127	27	158	2	189	----
128	28	159	4	190	----
129	20	160	60	192	92
130	30	161	61	193	93
131	37	162	62	194	----
131W	65				

Belt Interchange Chart Other Makes To G-C

Other Belt	G-C Belt	Other Belt	G-C Belt	Other Belt	G-C Belt
1	101	32	132	62	162
2	102	33	130	63	163
3	103	34	173	64	118
4	104	35	135	65	131W
5	105	36	136	66	127
6	177	37	137	67	140
7	107	38	138	68	169
8	108	39	144	69	138
9	109	40	139	70	170
10	109	41	138	71	171
11	104	42	140	72	172
12	112	43	143	73	175
13	112	44	144	74	176
14	114	45	145	75	168
15	115	46	146	76	167
16	116	47	147	77	168
17	117	48	151	78	154
18	118	49	149	79	133
19	123	50	170	80	117
20	120	51	184	81	179
21	121	52	152	82	181
22	122	53	153	83	148
23	126	54	154	84	167
24	124	55	107	85	182
25	125	56	156	86	183
26	126	57	157	87	170
27	127	58	101	88	174
28	128	59	114	89	165
29	180	60	160	90	166
30	130	61	161	91	193
31	134			92	194

Instructions For Measuring Belts

To determine size of belt, if the old belt is available, cut the belt and measure for stretched out length. This will be "cut length" of belt.

If old belt is not available or is worn out so that it cannot be properly measured, stretch a thin thread around belt pulleys on set. (Be sure to use thin thread as a thick cord will give an inaccurate reading.) Measure the thread, it will be our "Circumference Around Pulleys." In measuring belts always remember that the circumference around pulleys is not the same as stretched out or cut length. A belt when cut, develops approximately 3/16" extra length when stretched out, depending on thickness of belt.

G-C Belt Specifications Listed by Belt Number

G-C Belt	Circumference Around Pulleys	Cut Length	Models
101	6-23/32"	6-29/32"	Crowe, Dejur Amsco, Zenith
102	6-57/64"	7-5/64"	Crowe, Emerson, Kingston
103	7-15/32"	7-21/32"	Emerson
104	8-1/64"	8-13/64"	Emerson, Kingston
105	7-1/2"	7-11/16"	Crowe
106	7-1/4"	7-7/16"	Emerson, Majestic
107	7-11/16"	7-7/8"	Belmont, Crowe, Coronado
108	8-21/32"	8-27-32"	Acratest, Simplex
109	8-1/2"	8-11/16"	Fada, Acratest, Fairbanks-Morse, Majestic
110	8-25/64"	8-37/64"	Crowe, Fada
111	7-15/16"	8-1/8"	Goodyear, R.C.A.
112	8-43/64"	8-55/64"	Crowe R.C.A.
113	8-3/32"	8-9/32"	R.C.A.
114	8-15/64"	8-27/64"	Crowe, Emerson, Silvertone
115	9-13/64"	9-25/64"	Bosch, Lafayette, R.C.A., Silvertone
116	9-5/16"	9-1/2"	Crowe, R.C.A., Zenith
117	9-1/16"	9-1/4"	Crowe, Hallicrafters, McMurdo Silver, North Electric, Zenith
118	10-23/64"	10-35/64"	Emerson
119	9-17/32"	9-23/32"	Crowe, Garod, Hallicrafters, Scott
120	10-45/64"	10-57/64"	Garod, Sparton
121	10-11/16"	10-7/8"	Lafayette
122	10-3/8"	10-9/16"	R.C.A.
123	9-7/8"	10-1/16"	Airline, Lafayette
124	10-17/64"	10-29/64"	Garod, Westinghouse
125	10-25/64"	10-37/64"	Wilcox-Gay
126	9-61/64"	10-9/64"	Belmont, Coronado, Goodyear, Knight, Kingston, R.C.A.
127	9-59/64"	10-7/64"	Ultramar
128	10-19/64"	10-31/64"	Zenith
129	10-41/64"	10-53/64"	Bosch, R.C.A., Crowe, Zenith, Garod
130	11-5/64"	11-17/64"	Fada, Silver Marshall
131	11-9/64"	11-21/64"	Grunow, R.C.A., Ultramar
131W	11-9/32"	11-15/32"	Airline, Wells-Gardner
132	10-31/32"	11-5/32"	Coronado, Crosley, Grunow, Kingston
133	10-61/64"	11-9/64"	Zenith
134	11-3/8"	11-9/16"	Sparton

G-C Belt	Circumference Around Pulleys	Cut Length	Models
135	11"	11-3/16"	Truetone, Detrola
136	11-25/64"	11-37/64"	Belmont, Dejur Amsco, Detrola
137	11-5/32"	11-15/32"	Other Makes 37
138	11-57/64"	12-5/64"	Admiral, Fada, R.C.A., Zenith
139	12-9/32"	12-15/32"	Admiral, Lafayette, Zenith
140	12-7/32"	12-13/32"	Fairbanks-Morse, R.C.A.
141	11-3/4"	11-15/16"	Crosley, Dewald, Howard
142	12-3/32"	12-1/4"	Other Makes 54
143	11-13/16"	12"	Fairbanks-Morse
144	12-15/32"	12-21/32"	Crowe, Knight, Radio Products
145	12-39/64"	12-51/64"	Sparton, Grunow, Silvertone
146	13-3/16"	13-3/8"	Sparton
147	14-27/64"	14-39/64"	Arvin, Kingston, Sparton
148	14-33/64"	14-3/4"	Other Makes 83
149	15-1/64"	15-13/64"	Zenith, Grunow
150	15-61/64"	16-9/64"	Other Makes 85, Keystone R-8 Projector
151	14-57/64"	15-5/64"	Stromberg-Carlson
152	10-1/2"	10-11/16"	North Electric, Crowe, Scott
153	8-39/64"	8-51/64"	Belmont, Goodyear, Coronado
154	12-1/32"	12-7/32"	Crowe
155	7-35/64"	7-23/32"	Other Makes 3
156	7-9/32"	7-15/32"	Emerson
157	7-1/64"	7-13/64"	Capehart
158	6-15/16"	7-1/8"	Crosley
159	8-1/32"	8-7/32"	Airline, Coronado, Crowe, Emerson
160	8-11/16"	8-7/8"	Majestic, Zenith
161	6-55/64"	7-3/64"	Emerson, Majestic
162	8-13/64"	8-25/64"	Zephyr
163	9-19/64"	9-31/64"	Airline, Coronado, Wells-Gardner
164	10-1/4"	10-7/16"	Airline, Garod, Coronado, Wells-Gardner
165	17-1/16"	17-1/4"	Arvin
166	19-7/16"	19-5/8"	Arvin
167	8-13/16"	9"	Crowe, Zenith
168	12-13/16"	13"	Fairbanks-Morse, Keystone C-8 Projector, Zenith, Wells-Gardner
169	17-13/32"	17-19/32"	Admiral, Knight, Sonora
170	16-19/64"	16-31/64"	Admiral, Garod, Knight, Wells-Gardner
171	11-3/16"	11-3/8"	Other Makes 71
172	8-3/16"	8-3/8"	Other Makes 72
173	11-7/16"	11-5/8"	Fairbanks-Morse, Sparton
174	7-3/4"	7-15/16"	Emerson, General Electric
175	21-5/16"	21-1/2"	Majestic
176	22-35/64"	22-47/64"	Majestic
177	7-13/32"	7-19/32"	Majestic, R.C.A.
178	12-1/2"	12-11/16"	Case
179	17-37/64"	17-49/64"	Knight
180	10-27/32"	11-1/32"	Howard
181	18-9/16"	18-3/4"	Other Makes 82
182	15-13/16"	16"	Other Makes 85
183	15-7/16"	15-5/8"	Other Makes 86
184	16-27/64"	16-39/64"	Airline
185	16-15/16"	17-1/8"	Arvin
186	14-7/32"	14-13/32"	Coronado

G-C Belt	Circumference Around Pulleys	Cut Length	Models
187	15-17/64"	15-29/64"	Crowe, Garod
188	19-47/64"	19-59/64"	Crowe
189	18-1/2"	18-11/16"	Crowe
190	17-5/8"	17-13/16"	Crowe
191	22-49/64"	22-61/64"	Crowe
192	straight belt	16"	Airline, Wells-Gardner
193	straight belt	12-7/16"	Wells-Gardner
194	11-21/32"	11-27/32"	Truetone

G-C Belt Specifications Listed by Belt Size

Circumference Around Pulleys	Cut Length	G-C Belt	Models
6-23/32"	6-29/32"	101	Crowe, Dejur Amsco, Zenith
6-55/64"	7-3/64"	161	Emerson, Majestic
6-57/64"	7-5/64"	102	Crowe, Emerson, Kingston
6-15/16"	7-1/8"	158	Crosley
7-1/64"	7-13/64"	157	Capehart
7-1/4"	7-7/16"	106	Emerson, Majestic
7-9/32"	7-15/32"	156	Emerson
7-13/32"	7-19/32"	177	Majestic, R.C.A.
7-15/32"	7-21/32"	103	Emerson
7-1/2"	7-11/16"	105	Crowe
7-35/64"	7-23/32"	155	Other Makes 3
7-11/16"	7-7/8"	107	Belmont, Crowe, Coronado
7-3/4"	7-15/16"	174	Emerson, General Electric
7-15/16"	8-1/8"	111	Goodyear, R.C.A.
8-1/64"	8-13/64"	104	Emerson, Kingston
8-1/32"	8-7/32"	159	Airline, Coronado, Crowe, Emerson
8-3/32"	8-9/32"	113	R.C.A.
8-3/16"	8-3/8"	172	Other Makes 72
8-13/64"	8-25/64"	162	Zephyr
8-15/64"	8-27/64"	114	Crowe, Emerson, Silvertone
8-25/64"	8-37/64"	110	Crowe, Fada
8-1/2"	8-11/16"	109	Fada, Acratest, Fairbanks-Morse, Majestic
8-39/64"	8-51/64"	153	Belmont, Goodyear, Coronado
8-21/32"	8-27-32"	108	Acratest, Simplex
8-43/64"	8-55/64"	112	Crowe, R.C.A.
8-11/16"	8-7/8"	160	Majestic, Zenith
8-13/16"	9"	167	Crowe, Zenith
9-1/16"	9-1/4"	117	Crowe, Hallicrafters, McMurdo Silver, North Electric, Zenith
9-13/64"	9-25/64"	115	Bosch, Lafayette, R.C.A., Silvertone
9-19/64"	9-31/64"	163	Airline, Coronado, Wells-Gardner
9-5/16"	9-1/2"	116	Crowe, R.C.A., Zenith
9-17/32"	9-23/32"	119	Crowe, Garod, Hallicrafters, Scott
9-7/8"	10-1/16"	123	Airline, Lafayette
9-59/64"	10-7/64"	127	Ultramar
9-61/64"	10-9/64"	126	Belmont, Coronado, Goodyear, Knight, Kingston, R.C.A.

Circumference Around Pulleys	Cut Length	G-C Belt	Models
10-1/4"	10-7/16"	164	Airline, Garod, Coronado, Wells-Gardner
10-17/64"	10-29/64"	124	Garod, Westinghouse
10-19/64"	10-31/64"	128	Zenith
10-23/64"	10-35/64"	118	Emerson
10-3/8"	10-9/16"	122	R.C.A.
10-25/64"	10-37/64"	125	Wilcox-Gay
10-1/2"	10-11/16"	152	North Electric, Crowe, Scott
10-41/64"	10-53/64"	129	Bosch, R.C.A., Crowe, Zenith, Garod
10-11/16"	10-7/8"	121	Lafayette
10-45/64"	10-57/64"	120	Garod, Sparton
10-27/32"	11-1/32"	180	Howard
10-61/64"	11-9/64"	133	Zenith
10-31/32"	11-5/32"	132	Coronado, Crosley, Grunow, Kingston
11"	11-3/16"	135	Truetone, Detrola
11-5/64"	11-17/64"	130	Fada, Silver Marshall
11-9/64"	11-21/64"	131	Grunow, R.C.A., Ultramar
11-5/32"	11-15/32"	137	Other Makes 37
11-3/16"	11-3/8"	171	Other Makes 71
11-9/32"x5/16"	11-15/32"x5/16"	131W	Airline, Wells-Gardner
11-3/8"	11-9/16"	134	Sparton
11-25/64"	11-37/64"	136	Belmont, Dejur Amsco, Detrola
11-7/16"	11-5/8"	173	Fairbanks-Morse
11-21/32"	11-27/32"	194	Truetone
11-3/4"	11-15/16"	141	Crosley, Dewald, Howard
11-13/16"	12"	143	Fairbanks-Morse
11-57/64"	12-5/64"	138	Admiral, Fada, R.C.A., Zenith
12-1/32"	12-7/32"	154	Crowe
12-3/32"	12-1/4"	142	Other Makes 54
12-7/32"	12-13/32"	140	Fairbanks-Morse, R.C.A.
straight belt	12-7/16" str.belt	193	Wells-Gardner
12-9/32"	12-15/32"	139	Admiral, Lafayette, Zenith
12-15/32"	12-21/32"	144	Crowe, Knight, Radio Products
12-1/2"	12-11/16"	178	Case
12-39/64"	12-51/64"	145	Sparton, Grunow, Silvertone
12-13/16"	13"	168	Fairbanks-Morse, Keystone C-8 Projector, Zenith, Wells-Gardner
13-3/16"	13-3/8"	146	Sparton
14-7/32"	14-13/32"	186	Coronado
14-27/64"	14-39/64"	147	Arvin, Kingston, Sparton
14-33/64"	14-3/4"	148	Other Makes 83
14-57/64"	15-5/64"	151	Stromberg-Carlson
15-1/64"	15-13/64"	149	Zenith, Grunow
15-17/64"	15-29/64"	187	Crowe, Garod
15-7/16"	15-5/8"	183	Other Makes 86
15-13/16"	16"	182	Other Makes 85
straight belt	16" straight belt	192	Airline, Wells-Gardner
15-61/64"	16-9/64"	150	Keystone R-8 Projector, Other Makes 85
16-19/64"	16-31/64"	170	Admiral, Garod, Knight, Wells-Gardner
16-27/64"	16-39/64"	184	Airline
16-15/16"	17-1/8"	185	Arvin
17-1/16"	17-1/4"	165	Arvin
17-13/32"	17-19/32"	169	Admiral, Knight, Sonora
17-37/64"	17-49/64"	179	Knight

Circumference Around Pulleys	Cut Length	G-C Belt	Models
17-5/8"	17-13/16"	190	Crowe
18-1/2"	18-11/16"	189	Crowe
18-9/16"	18-3/4"	181	Other Makes 82
19-7/16"	19-5/8"	166	Arvin
19-47/64"	19-59/64"	188	Crowe
21-5/16"	21-1/2"	175	Majestic
22-35/64"	22-47/64"	176	Majestic
22-49/64"	22-61/64"	191	Crowe

JFD Belt Specifications

Belt Interchange Chart JFD to Other Makes

Use J.F.D. No.	In Place of Other Belt Nos.	Use J.F.D. No.	In Place of Other Belt Nos.	Use J.F.D. No.	In Place of Other Belt Nos.
1	101	34	173	67	139
2	161	35	135	68	169
3	103-155	36	194	69	138
4	104-159	37	137	70	170
5	105	38	138	71	171
6	177	39	144	72	113
7	174	40	178	73	175
8	108	41	143	74	176-191
9	109	42	140	75	168
10	109	43	141	76	167
11	111	44	145	77	168
12	153	45	145	78	154
13	108	46	146	79	133
14	110	47	147-186	80	115
15	116	48	151	81	179-190
16	119	49	149-187	82	181-189
17	117	50	184	83	148
18	118	51	184	84	167
19	123	52	152	85	150-182
20	121-129	53	112	86	183
21	120	54	142	87	170
22	152	55	107	88	174
23	126	56	106-156	89	165-185
24	124-164	57	157	90	166-188
25	122	58	158	91	193
26	126	59	172		
27	127	60	160		wide open
28	128	61	102	92	192
29	180	62	114-162		
30	134	63	163		wide open
31	136	64	125	93	185
32	130-132	65	131W	94	147
33	131	66	123	95	136

Belt Interchange Chart Other Makes to JFD

In Place of Other Belt Nos.	Use J.F.D. No.	In Place of Other Belt Nos.	Use J.F.D. No.	In Place of Other Belt Nos.	Use J.F.D. No.
101	1	133	79	166	90
102	61	134	30	167	84
103	3	135	35	168	77
104	4	136	95	169	68
105	5	137	37	170	87
106	56	138	38	171	71
107	55	139	67	172	59
108	13	140	42	173	34
109	10	141	43	174	7
110	14	142	54	175	73
111	11	143	41	176	74
112	53	144	39	177	6
113	72	145	44	178	40
114	62	146	46	179	81
115	80	147	94	180	29
116	15	148	83	181	82
117	17	149	49	182	85
118	18	150	85	183	86
119	16	151	48	184	50
120	21	152	22	185	93
121	20	153	12	186	47
122	25	154	78	187	49
123	66	155	3	188	90
124	24	156	56	189	82
125	64	157	57	190	81
126	26	158	58	191	74
127	27	159	4	192	92
128	28	160	60		
129	20	161	2	wide open	
130	32	162	62	193	91
131	33	163	63		
131W	65	164	24	wide open	
132	32	165	89	194	36

Instructions For Measuring Belts

In order to determine the size of a belt, if the old belt is available, cut this belt and measure its length when stretched out. This will give you the "Length When Open".

If the old belt is not available or cannot be measured because of its worn condition, stretch a thin thread around the belt pulleys within the set. The measurement of this thread will give you the "Inside Pulley Circumference". This is not to be confused with the "Length When Open". The belt when cut will be approximately 3/16" longer when stretched out.

JFD Belt Specifications Listed by Belt Number

JFD Belt	Inside Pulley Circumference	Length When Open	Models
1	6-5/8"	8-13/16"	Dejur Amsco, Zenith
2	6-13/16"	7"	Crosley, Crowe, Emerson, Kingston, Majestic, Zenith
3	7-17/32"	7-23/32"	Emerson
4	8-3/32"	8-9/32"	Belmont, Fairbanks-Morse, Kingston
5	7-9/16"	7-3/4"	Crowe
6	7-13/32"	7-19/32"	Majestic, R.C.A.
7	7-23/32"	7-23/32"	Belmont, Crowe
8	8-9/16"	8-3/4"	Acratest, Simplex
9	8-17/32"	8-23/32"	Acratest, Fairbanks-Morse
10	8-1/2"	8-11/16"	Fada
11	7-29/32"	8-3/32"	Emerson, R.C.A.
12	8-19/32"	8-25/32"	Majestic, R.C.A.
13	8-5/8"	8-13/16"	Airline, Crowe, R.C.A.
14	8-7/16"	8-5/8"	Fada, Silvertone
15	9-5/16"	9-1/2"	Bosch, Lafayette, R.C.A.
16	9-7/16"	9-5/8"	Airline, Crowe, Garod, Zenith
17	9-5/32"	9-11/32"	Crowe, Simplex, Zenith, Zephyr
18	10-15/32"	10-21/32"	Emerson
19	9-13/16"	10"	Garod
20	10-11/16"	10-7/8"	Garod, Philco
21	10-3/4"	10-15/16"	Lafayette
22	10-1/2"	10-11/16"	R.C.A.
23	10-1/3"	10-7/32"	Airline, R.C.A.
24	10-5/16"	10-1/2"	Westinghouse
25	10-15/32"	10-21/32"	Wilcox-Gray
26	10-1/16"	10-1/4"	Belmont, Knight, Lafayette, Ultramar
27	9-15/16"	10-1/8"	Airline, Belmont
23	10-13/32"	10-19/32"	Zenith
29	10-13/16"	11"	Bosch, Fada
30	11-1/4"	11-7/16"	Grunow, Silver-Marshall
31	11-5/16"	11-1/2"	Wells-Gardner
32	11-1/16"	11-1/4"	Fairbanks-Morse, Grunow, Kingston
33	11-5/32"	11-11/32"	R.C.A.
34	11-1/2"	11-11/16"	Sparton
35	11-3/32"	11-9/32"	Detrola
36	11-9/16"	11-3/4"	Crosley, Dejur Amsco, Detrola
37	11-9/32"	11-15/32"	Fada

JFD Belt	Inside Pulley Circumference	Length When Open	Models
38	12"	12-3/16"	Zenith
39	12-7/16"	12-5/8"	Admiral, Crowe
40	12-5/16"	12-1/2"	Fairbanks-Morse, Lafayette, Zenith
41	11-15/16"	12-1/8"	Dewald, Fada
42	12-7/32"	12-13/32"	R.C.A.
43	11-7/8"	12-1/16"	R.C.A.
44	12-9/16"	12-3/4"	Case, Knight
45	12-11/16"	12-7/8"	Silvertone
46	13-1/8"	13-5/16"	Fairbanks-Morse, Sparton, Wells-Gardner, Zenith
47	14-1/2"	14-11/16"	Kingston, Sparton
48	14-27/32"	15-1/32"	Arvin, R.C.A., Stromberg-Carlson
49	15-5/32"	15-11/32"	Zenith
50	16-7/16"	16-5/8"	Knight, R.C.A., Wells-Gardner
51	16-1/2"	16-11/16"	Airline
52	10-9/16"	10-3/4"	Garod, Grunow, North Electric
53	8-11/16"	8-7/8"	Belmont, Majestic
54	12-1/16"	12-1/4"	Fairbanks-Morse
55	7-11/16"	7-7/8"	Crowe
56	7-9/32"	7-15/32"	Emerson
57	7-3/32"	7-9/32"	Capehart
58	6-3/4"	6-15/16"	Crosley
59	8-3/16"	8-3/8"	Crowe, Emerson
60	8-3/4"	8-15/16"	Majestic, Zenith
61	6-29/32"	7-3/32"	Emerson, Majestic
62	8-1/4"	8-7/16"	Airmaster, Emerson
63	9-3/8"	9-9/16"	Airline, Wells-Gardner
64	10-3/18"	10-9/16"	Airline, Wells-Gardner
65	11-3/16"	11-3/8"	Airline
66	9-7/8"	10-1/16"	Coronada
67	12-1/4"	12-7/18"	Admiral
68	17-7/16"	17-5/8"	Admiral, Knight
69	11-29/32"	12-3/32"	Admiral, Knight
70	16-15/32"	16-21/32"	Wells-Gardner
71	11-3/16"	11-3/8"	Ultramar
72	8-9/32"	8-15/32"	Emerson
73	21-1/16"	21-1/4"	Majestic
74	22-9/16"	22-3/4"	Majestic
75	12-15/16"	13-1/8"	Sparton
76	8-15/16"	9-1/8"	Zenith
77	12-7/8"	13-1/16"	Zenith
78	12-1/32"	12-7/32"	Crowe
79	11"	11-3/16"	Zenith
80	9-3/16"	9-3/8"	Zenith
81	17-9/16"	17-3/4"	Wells-Gardner
82	18-9/16"	18-3/4"	Wells-Gardner
83	14-9/16"	14-3/4"	Wells-Gardner
84	8-13/16"	9"	Zenith
85	15-13/16"	16"	Garod
86	15-7/16"	15-5/8"	Garod
87	16-3/16"	16-3/8"	Admiral
88	7-13/16"	8"	General Electric
89	16-13/16"	17"	Arvin, Garod
90	19-9/16"	19-3/4"	Arvin

JFD Belt	Inside Pulley Circumference	Length When Open	Models
91	12-1/4"	12-7/16"	Wells-Gardner
92	15-13/16"	16"	Airline
93	16-15/16"	17-1/8"	Arvin
94	14-27/64"	14-39/64"	Arvin
95	11-25/64"	11-37/64"	Kingston, Belmont, Dejur Amsco, Detrola

JFD Belt Specifications Listed by Belt Size

Inside Pulley Circumference	Length When Open	JFD Belt	Models
6-5/8"	6-13/16"	1	Dejur Amsco, Zenith
6-3/4"	6-15/16"	58	Crosley
6-13/16"	7"	2	Crosley, Crowe, Emerson, Kingston, Majestic, Zenith
6-29/32"	7-3/32"	61	Emerson, Majestic
7-3/32"	7-9/32"	57	Capehart
7-9/32"	7-15/32"	56	Emerson
7-13/32"	7-19/32"	6	Majestic, R.C.A.
7-9/16"	7-3/4"	5	Crowe
7-17/32"	7-23/32"	3	Emerson
7-11/16"	7-7/8"	55	Crowe
7-23/32"	7-29/32"	7	Belmont, Crowe
7-13/16"	8"	88	General Electric
7-29/32"	8-3/32"	11	Emerson, R.C.A.
8-3/32"	8-9/32"	4	Belmont, Fairbanks-Morse, Kingston
8-3/16"	8-3/8"	59	Crowe, Emerson
8-1/4"	8-7/16"	62	Airmaster, Emerson
8-9/32"	8-15/32"	72	Emerson
8-7/16"	8-5/8"	14	Fada, Silvertone
8-9/16"	8-3/4"	8	Acratest, Simplex
8-1/2"	8-11/16"	10	Fada
8-17/32"	8-23/32"	9	Acratest, Fairbanks-Morse
8-19/32"	8-25/32"	12	Majestic, R.C.A.
8-5/8"	8-13/16"	13	Airline, Crowe, R.C.A.
8-11/16"	8-7/8"	53	Belmont, Majestic
8-3/4"	8-15/16"	60	Majestic, Zenith
8-13/16"	9"	84	Zenith
8-15/16"	9-1/8"	76	Zenith
9-3/16"	9-3/8"	80	Zenith
9-5/32"	9-11/32"	17	Crowe, Simplex, Zenith, Zephyr
9-5/16"	9-1/2"	15	Bosch, Lafayette, R.C.A.
9-3/8"	9-9/16"	63	Airline, Wells-Gardner
9-7/16"	9-5/3"	16	Airline, Crowe, Garod, Zenith
9-13/16"	10"	19	Garod
9-7/8"	10-1/16"	66	Coronado
9-15/16"	10-1/8"	27	Airline, Belmont
10-1/32"	10-7/32"	23	Airline, R.C.A.
10-1/16"	10-1/4"	26	Belmont, Knight, Lafayette, Ultramar
10-5/16"	10-1/2"	24	Westinghouse
10-3/16"	10-9/16"	64	Airline, Wells-Gardner

Inside Pulley Circumference	Length When Open	JFD Belt	Models
10-13/32"	10-19/32"	28	Zenith
10-15/32"	10-21/32"	18	Emerson
10-15/32"	10-21/32"	25	Wilcox-Gray
10-1/2"	10-11/16"	22	R.C.A.
10-9/16"	10-3/4"	52	Garod, Grunow, North Electric
10-11/16"	10-7/8"	20	Garod, Philco
10-3/4"	10-15/16"	21	Lafayette
10-13/16"	11"	29	Bosch
11"	11-3/16"	79	Zenith
11-1/16"	11-1/4"	32	Grunow, Fairbanks-Morse, Kingston
11-3/32"	11-9/32"	35	Detrola
11-5/32"	11-11/32"	33	R.C.A.
11-3/16"	11-3/8"	65	Airline
11-3/16"	11-3/8"	71	Ultramar
11-1/4"	11-7/16"	30	Fada, Grunow, Silver-Marshall
11-9/32"	11-15/32"	37	Fada
11-5/16"	11-1/2"	31	Wells-Gardner
11-25/64"	11-37/64"	95	Belmont, Dejur Amsco, Detrola
11-1/2"	11-11/16"	34	Sparton
11-9/16"	11-3/4"	36	Crosley, Dejur Amsco, Detrola
11-7/8"	12-1/16"	43	R.C.A.
11-29/32"	12-3/32"	69	Admiral, Knight
11-15/16"	12-1/8"	41	Dewald, Fada
12"	12-3/16"	38	Zenith
12-1/32"	12-7/32"	78	Crowe
12-1/16"	12-1/4"	54	Fairbanks-Morse
12-7/32"	12-13/32"	42	R.C.A.
12-1/4"	12-7/16"	67	Admiral
12-1/4"	12-7/16"	91	Wells-Gardner
(Open wide belt)			
12-5/16"	12-1/2"	40	Fairbanks-Morse, Lafayette, Zenith
12-7/16"	12-5/8"	39	Admiral, Crowe
12-9/16"	12-3/4"	44	Case, Knight
12-11/16"	12-7/8"	45	Silvertone
12-7/8"	13-1/16"	77	Zenith
12-15/16"	13-1/8"	75	Sparton
13-1/8"	13-5/16"	46	Fairbanks-Morse, Sparton, Wells-Gardner, Zenith
14-27/64"	14-39/64"	94	Arvin, Kingston
14-1/2"	14-11/16"	47	Kingston, Sparton
14-9/16"	14-3/4"	83	Wells-Gardner
14-27/32"	15-1/32"	48	Arvin, R.C.A., Stromberg-Carlson
15-5/32"	15-11/32"	49	Zenith
15-7/16"	15-5/8"	86	Garod
15-13/16"	16"	85	Garod
15-13/16"	16"	92	Airline
(Open wide belt)			
16-3/16"	16-3/8"	87	Admiral
16-7/16"	16-5/8"	50	Knight, R.C.A., Wells-Gardner
16-15/32"	16-21/32"	70	Wells-Gardner
16-1/2"	16-11/16"	51	Airline
16-13/16"	17"	89	Arvin, Garod
16-15/16"	17-1/8"	93	Arvin
17-7/16"	17-5/8"	68	Admiral, Knight

Inside Pulley Circumference When Open	Length	JFD Belt	Models
17-9/16"	17-3/4"	81	Wells-Gardner
18-9/16"	18-3/4"	82	Wells-Gardner
19-9/16"	19-3/4"	90	Arvin
21-1/16"	21-1/4"	73	Majestic
22-9/16"	22-3/4"	74	Majestic